

PORTABLE PERMANENT SIGNAL LOCKOUT SET

1. GENERAL

1.01 This appendix describes the permanent signal lockout set DA-30091-11 for use in line finder step-by-step central offices.

1.02 (Reserved for future use)

2. PURPOSE OF CIRCUIT

2.01 The set provides the means to lock out a permanent signal condition to free the line finder and first selector.

3. FUNCTIONS

3.01 The set is portable and may be hung on a permanently mounted bracket at each line finder group.

3.02 It is equipped with two cords. One for battery and ground, the other for attaching the

set to the line circuit at the line finder terminal strip.

3.03 When attached to a subscriber's line circuit, which is on permanent signal, the push button of the set operates the PS relay. Relay PS operated, locks through its own contacts under control of the subscriber's loop. It also places ground on the sleeve of the subscriber's line, and extinguishes the lockout set lamp. The line finder may now be released.

3.04 If the subscribers' line is cleared, the PS relay releases. PS relay released, removes ground from sleeve, disconnects from line and lockout set lamp lights.

3.05 The circuit is arranged to indicate the presence of the lockout set when the line is tested from the test desk.

3.06 The set can be cleared from the line by use of the PS RLS key at the test desk.

NOTICE

Not for use or disclosure outside the
Bell System except under written agreement