

TRENDLINE, ROTARY DIAL, DESK TELEPHONES

REPLACEMENT PARTS

1. GENERAL

1.01 This document covers the Trendline, rotary dial, desk telephone. (See Figure 1.) An exploded-view drawing of the telephone with major assembly groups (see Figure 2) and a replacement parts list (see Table A) are included.

1.02 This section is reissued to remove manufacturing discontinued versions of the telephone and to add features for the full-modular (M) version telephones. Issue 2 corrected errors in the initial issue.

Note: Ordering information for manufacturing discontinued telephones has been removed; however, descriptive information has been retained as a reference for telephones still in service.

1.03 For additional information on description and installation of the telephones, refer to Section 50-200-100. The circuit labels appear in Section 50-200-102. Related documents of the CORTELCO Telephone Apparatus Practices Manual provide information on components.

1.04 The Model 200 desk telephones are Trendline, rotary dial, anti-sidetone type units that operate efficiently over a wide range of loop resistances and line impedances.

1.05 The Model 200 desk telephones are identified by a coded label affixed to the bottom of the base. Refer to Section 50-200-100 of the CORTELCO Telephone Apparatus Practices Manual for ordering information and for an explanation of each code number.



AW82-465

Fig. 1 Trendline, Rotary Dial, Desk Telephone

TABLE A
REPLACEMENT PARTS LIST

INDEX NO	PART NUMBER	DESCRIPTION	QUANTITY USED
		Trendline, Rotary Dial, Desk Telephone	200/20
1	0220**-20M	Handset Assembly	1
2	087514-101	Retainer, Number Card	1
3	087513-101	Card, Number	1
	087513-102	Card, Number, Strip Of 6 (Not Shown)	1
4	088593-101	Shield, Light	1
5	600017-204-004	Screw, PH	2
6	088707-0**	Housing, Handset	1
7	088701-0**	Button, Recall	1
8	001000-00G	Dial Assembly, Metropolitan (Letters And Numerals) ¹	1
	180308-101	Card, Number (For Dial Finger Wheel, Not Shown)	1
	180314-101	Insert, Finger Wheel (Plastic Card Cover, Not Shown)	1
9	096407-102	Screw, Dial Mounting	3
10	088704-101	Gasket, Receiver	1
11	187120-102	Receiver	1
12	088706-101	Gasket	2
13	183927-101	Cup Assembly, Receiver	1
14	180245-102	Screw, Cup Assembly Mounting	2
15	096405-101	Lamp ⁵	1
16	183092-101	Housing, Lamp	1
17	088718-0**	Cover, Handset	1
18	096407-102	Screw	2
19	088719-102	Bracket, Retainer L. H.	1
20	088719-101	Bracket, Retainer R. H.	1
21	184130-101	Modular Network Assembly	1
22	075555-101	Transmitter	1
23	088705-101	Gasket, Transmitter	1
24	0AG1**-OBA	Base And Housing Assembly (Nonmodular) ³	1
24	0AG1**-OLR	Base And Housing Assembly (Nonmodular, Less Ringer) ³	1
24	0AG1**-FBA	Base And Housing Assembly (Full-Modular) ³	1
24	0AG1**-FLR	Base And Housing Assembly (Full-Modular, Less Ringer) ³	1
24	0AG1**-MBA	Base And Housing Assembly (Full-Modular With Cord)	1
24	0AG1**-MLR	Base And Housing Assembly (Full-Modular With Cord, Less Ringer) ³	1
25	184566-101	Base Assembly	1
		Plastic Base (Not Shown) ²	1
	184655-101	Threaded Insert (Not Shown)	1
26	184406-101	Insulator Assembly	1
27	184514-101	Arm, Lever	1
28	187962-101	Spring, Lever Arm	1
29	184519-101	Pin, Pivot	1
30	184550-102	Cradle Switch Assembly ¹	1
31	184518-101	Terminal Board Assembly	1
32	095995-103	Capacitor	1
33	088554-0**	Nameplate	1
34	095992-102	Screw, Base Housing	2
35	088773-101	Plunger	1
36	184249-0**	Housing Base	1
37	000153-ABA	Ringer ^{1, 4}	1
37	000153-PBA	Ringer ^{1, 4}	1
38	182988-101	Modular Jack Assembly	1

TABLE A
REPLACEMENT PARTS LIST (Cont)

INDEX NO	PART NUMBER	DESCRIPTION	QUANTITY USED
		Trendline, Rotary Dial, Desk Telephone	200/20
39	182990-101	4-Pin Insulator Assembly	1
40	184549-101	Foot	4
	079485-102	Screw (Not Shown)	1
	096407-102	Screw (Not Shown)	1
	180221-106	Screw (Not Shown)	1
41	9018**-072	Cord, Coiled	1
42	182827-084	Cord, Line (Modular)	1
43	185684-084	Cord, Line (Nonmodular) ³	1
	000031-101	Transformer, Power (Not Shown) ⁵	1

AW89-78

Notes:

** Substitute 2-Digit Color Code When Ordering.

¹ Refer To Component Parts Section Of This Manual For Assembly Parts List.

² This Is An NSS Item (Not Serviced Separately).

³ These Products Have Been Discontinued, But Are Included To Provide A Source Of Information For Telephones Still In Service.

⁴ The 000153-PBA Ringer Replaces The 000153-ABA Ringer.

⁵ This part must be ordered separately.