



Acer Iconia Tab 8 A1-860 Motherboard Replacement

This guide will assist you in removing the motherboard from your Acer Iconia A1-860 tablet.

Written By: Michael Buchanan



INTRODUCTION

Most components either connect or interface with the motherboard in some way. Because there is a lot involved, this guide shows how to remove it properly.

TOOLS:

- [iFixit Opening Tools](#) (1)
 - [Spudger](#) (1)
 - [Phillips #00 Screwdriver](#) (1)
 - [Phillips #000 Screwdriver](#) (1)
 - [Tweezers](#) (1)
 - [iOpener](#) (1)
-

Step 1 — Rear Case



- Insert the plastic opening tool into the seam between the back case and the display.
- Work the plastic opening tool around the seam until the rear case separates from the display.

Step 2




- Separate the rear case and place the tablet face side down.

Step 3 — Battery




- Using a spudger, work the tool under the battery connector located above the battery on the left side, and lift it free.

Step 4




- Pull firmly on the black tabs, located at the top left and bottom right of the battery.
- ⓘ The clear adhesive strips attached to the tabs are quite stretchy. Don't give up; keep pulling the tabs until the battery releases. The strips will not be reusable.
- Remove the battery.

Step 5 — Motherboard





- Using the spudger, remove the two tabs shown by placing the spudger under the gray part of the connectors and pulling on the tabs.

Step 6





- Use a Phillips #00 screwdriver to remove the three 2 mm screws.

Step 7




- Using the spudger, push the tab where this belt connects to the motherboard to free it.
- Use tweezers in order to pull the belt from its slot in the motherboard.

Step 8



- Using the spudger, push the tab connecting this belt to the motherboard.
- Once the tab is pushed and the belt is free to move, use tweezers to pull it from the slot.

Step 9




- Using tweezers, pull upward on the end of this belt where it plugs into the motherboard.

Step 10




- With the tweezers, grab the gray wire and move it from underneath the plastic piece shown in red.
- Then place the tweezers on the end of the wire circled, and pull the piece from the motherboard.

Step 11





- Use tweezers in order to lift a corner of this copper foil.
- Then use a spudger to pull the copper foil from the motherboard.
- ⓘ If the copper foil does not remove easily, use an iOpener heating pad to release the adhesive.

Step 12



- Using tweezers, remove the "void" sticker to reveal a 3 mm screw.
- Use a Phillips #000 screwdriver to remove the three 3 mm screws.

Step 13



- Carefully lift the motherboard out of its slot in the rear case.

To reassemble your device, follow these instructions in reverse order.