



# PlayStation 2 Slimline Teardown

This guide will walk you through the steps of disassembling and reassembling a playstation 2 slim.  
A step by step guide with pictures.

Written By: kempc8



## INTRODUCTION

This guide will walk you through the steps of disassembling and reassembling a playstation 2 slim. A step by step guide with pictures.

---

### TOOLS:


- [Phillips #00 Screwdriver](#) (1)
  - [Spudger](#) (1)
  - [Tweezers](#) (1)
  - [Magnetic Project Mat](#) (1)
  - [ESD Gloves](#) (1)
  - [Anti-Static Mat](#) (1)
-

## Step 1 — Let's get started



- Start with the console upside down.

## Step 2




- Remove the six screw covers and place on project mat.
- Remove the six 4.0 mm screws on the base of the PS2. (Place on your project mat.)

### Step 3





- Separate the bottom of PS2 from the top. Place to the side.

### Step 4






- "This PS2 that I am tearing down has no clock battery!!"
- Locate the clock battery. Take tweezers and gently disconnect from motherboard. (Place on project mat)

## Step 5





- IR sensor on the motherboard.
- Gently use a spudger to release the blue/ white ribbon from motherboard, (Place IR sensor on project mat)

## Step 6




- Fan has red, black, and yellow wires under hold down tape. Remove the tape gently.
- Release the connector gently from motherboard.
- There three 1.6 mm screws around the base of the fan. Place both fan and screws on your project mat.

## Step 7




- Optical drive on the motherboard
- There are four 4.0 mm screws holding the optical drive.
- Remove the four screws and place the optical drive with its screws on your project mat.

## Step 8





- There is a ribbon attached to the motherboard here. With your spudger, gently detach the ribbon from the motherboard's connection.

## Step 9




- Remove the single 2.4 mm screw located on the metal casing at the top of the motherboard.

## Step 10





- Gently lift the metal casing from the motherboard. Place it to the side.

## Step 11



- Flip the motherboard over and remove the five screws of the second metal casing.
- Place screws on project mat and casing to the side,

## Step 12



- Motherboard of PS2
- Thank you for reading through this PS2 tear down. I hope this was helpful,