



AT&T 585-305-532
Issue 1
November 1993
Comcode 107092710

AUDIX®
Announcement Customization
Standard User Interface

**Copyright © 1995 AT&T
All Rights Reserved
Printed in U.S.A.**

Notice

While reasonable efforts were made to ensure that the information in this document was complete and accurate at the time of printing, AT&T can assume no responsibility for any errors. Changes and corrections to the information contained in this document may be incorporated into future reissues.

Your Responsibility for Your System's Security

You are responsible for the security of your system. AT&T does not warrant that this product is immune from or will prevent unauthorized use of common-carrier telecommunication services or facilities accessed through or connected to it. AT&T will not be responsible for any charges that result from such unauthorized use. Product administration to prevent unauthorized use is your responsibility and your system administrator should read all documents provided with this product to fully understand the features available that may reduce your risk of incurring charges.

Federal Communications Commission Statement

Part 15: Class A Statement. This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio-frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference, in which case the user will be required to correct the interference at his or her own expense.

Part 68: Network Registration Number. This equipment is registered with the FCC in accordance with Part 68 of the FCC Rules. It is identified by FCC registration number AS593M-14695-MA-E.

Trademarks

AUDIX is a registered trademark of AT&T.

Ordering Information

The ordering number for this document is 585-305-532. To order this document, call the GBCS Publications Fulfillment Center at 1-800-457-1235 (International callers use 1-317-361-5353). For more information about AT&T documents, refer to the *Global Business Communications Systems Publications Catalog* (555-000-010).

Comments

To comment on this document, return the comment card at the front of the document.

Acknowledgment

This document was prepared by the AT&T Product Documentation Development Department, Denver, CO 80234-2703.

Contents

About This Document	v
INTENDED AUDIENCE	v
HOW THIS DOCUMENT IS ORGANIZED	v
HOW TO USE THIS DOCUMENT	vi
CONVENTIONS USED IN THIS DOCUMENT	vi
HOW TO MAKE COMMENTS ABOUT THIS DOCUMENT	vi
1. Overview	1-1
ANNOUNCEMENT SETS	1-1
Announcements and Fragments	1-1
Active and Administrative Announcement Sets	1-2
ANNOUNCEMENT CUSTOMIZATION PROCESS	1-3
2. Announcement Customization Procedures	2-1
To Re-record a Fragment	2-1
To Delete a Fragment from an Announcement	2-4
To Add a Fragment to an Announcement	2-5
3. Post-Upgrade Procedures	3-1
Verify Customization Impact	3-1
Create a New Administrative Version	3-5
Restore Customized Fragments	3-6

A. Standard Announcements	A-1
B. Standard Fragments	B-1
C. Fragment/Announcement Cross-Reference	C-1
Index	IN-1

LIST OF TABLES


Table 3-1. R1V8 Announcement Composition (<i>Page 1 of 2</i>)	3-3
---	-----

About This Document

This document describes how to customize system announcements (prompts and messages) on an AT&T AUDIX Voice Messaging System. This document should *only* be used for AUDIX systems that are running Release 1 Version 8 (R1V8) software with the *standard* announcement set, sometimes called the Streamlined User Interface.

INTENDED AUDIENCE

This document is intended for system administrators who need to customize (modify or re-record) AUDIX announcements on an AUDIX system that is running R1V8 software.



Because one AUDIX fragment (spoken word or phrase) may affect many system announcements, it is strongly recommended that system administrators obtain training or consult their AT&T representative prior to changing any system announcements (customers may be charged for this service).

HOW THIS DOCUMENT IS ORGANIZED

This document is organized as follows:

- Chapter 1, *Overview*, describes the role of announcements and fragments in creating AUDIX system prompts and messages.
- Chapter 2, *Announcement Customization Procedures*, details the steps for re-recording, changing, or deleting AUDIX system announcements and fragments.
- Chapter 3, *Post-Upgrade Procedures*, covers the steps needed to restore customized announcements and/or fragments following an upgrade to R1V8 software.
- Appendix A, *Standard Announcements*, lists the AUDIX system announcements in the standard announcement set and the fragments that compose them.
- Appendix B, *Standard Fragments*, lists the fragments in the standard announcement set.
- Appendix C, *Fragment/Announcement Cross-Reference*, presents a list of fragment numbers followed by the numbers of all system announcements that use (and would be affected by changes to) that fragment.

An index appears at the end of this document.

HOW TO USE THIS DOCUMENT

Read the overview, then follow the steps in Chapter 2 or Chapter 3 as needed. This document is intended to be used in conjunction with the *AUDIX Administration* (585-305-501) and *AUDIX Release 1 Version 8 Forms Reference* (585-305-209).

CONVENTIONS USED IN THIS DOCUMENT

The following typographic conventions are used in this document:

- Information that appears on your terminal screen (including displays, field names, prompts, and error messages) is shown in constant-width type. Information that you are to type just as it appears in the document is shown in constant-width bold type. For example:

At the `when?` prompt, type **`now`**

- Terminal keys that you are to press are shown in boxes. For example, an instruction to press the return, carriage return, or equivalent key might appear in this document as:

Press `RETURN`.

- Two or three keys that you are to press at the same time (that is, you are to hold down the first key while pressing the second key and, if appropriate, the third key as well) are enclosed together, separated by hyphens, in a curved-edge box. For example, an instruction to press and hold the `ALT` key while typing the letter `d` appears in this document as:

Press `ALT-d`.

- Variables for which you or the system substitute a word specific to your own application are shown in italic type. For example, an error message that appears on the screen with the name of your own specific filename might appear generically in this document as:

Your file *filename* is formatted incorrectly.

HOW TO MAKE COMMENTS ABOUT THIS DOCUMENT

While we have tried to make this document fit your needs, we are interested in your suggestions for improving it. If the reader comment card has been removed from this document, please send your comments to:

AT&T
Product Documentation Development Department
11900 North Pecos Street
Room 22-2C11
Denver, Colorado 80234

1. Overview

AUDIX system *announcements* are the voiced (spoken) prompts and messages that the AUDIX system plays for subscribers, callers, and administrators who access the AUDIX system. Announcements are made of up one or more *fragments*. A fragment is a piece of voice text consisting of an individually recorded word, phrase, or sentence.

This chapter describes how the AUDIX system combines fragments to make system announcements, and gathers the announcements into different *announcement sets* (filesystems) that may be altered by the system administrator.

ANNOUNCEMENT SETS

An *announcement set* is a filesystem that contains all the announcements (prompts and other system messages) that may be encountered by the user. Two versions of the AUDIX system announcements are available with the R1V8 software release:

- *Standard* — The default version of system announcements on R1V8 systems, sometimes called the Streamlined User Interface. This version is typically named `disk00.ana` on a new system or `ana.adat` on a generic cartridge. The standard announcements are often more concise than the traditional set and are consistent with the standard announcement set available with the DEFINITY AUDIX voice mail system.
- *Traditional* — The traditional (abbreviated) version of system announcements designed to make upgrades to the R1V8 software release as transparent as possible for subscribers accustomed to using an earlier AUDIX software release. This version is typically named `disk00.anc` on a new system or `anc.adat` on a generic cartridge. However, if an AUDIX system is upgraded to R1V8 software from an earlier release, the announcement filesystem will use the same name and disk location as the previous announcement set (for example, `disk02.anc`).

If you are using this guide, you should have the *standard* version of announcements installed on your system. To verify the standard announcements are active, record any AUDIX message and listen to the prompt. If it tells you to press (#) to approve the message (instead of (* #)), the standard announcement set is installed.

Announcements and Fragments

Each system announcement is identified by a number and contains up to nine system fragments consisting of a word, phrase, or sentence. Fragments are also identified by number. A single fragment or several fragments can be used to compose an announcement. Announcements determine the number and order of fragments as they will be encountered by the user.

For example, refer to Appendix A, *Standard Announcements*. It indicates that system announcement number 10 is composed of fragment number 16, “*Please enter announcement ID*”, and fragment number 224, “*followed by the pound sign*”.

Appendix B, *Standard Fragments*, lists the fragments in numerical order, allowing you to easily check the text of any given fragment.

Appendix C, *Fragment/Announcement Cross-Reference*, shows all the announcements in which a given fragment is used. Changing a fragment in one announcement could cause an unintentional change in another announcement if you aren’t careful.



If you decide to change your system announcements, you must be extremely careful and precise. If you make a mistake, the resulting announcements could be erroneous, and straightening out mistakes can be frustrating and time-consuming. It is strongly recommended that you do not attempt to modify any announcements without the help of your AT&T representative (you may be charged for this service).

Active and Administrative Announcement Sets

Only one announcement set can be active (accessible to users) at a time. The `system : announcement : filesystems` form shows the name of the *active* announcement set. The *active* designation means that this is the announcement set that will be heard by anyone who accesses the AUDIX system.

The `system : announcement : filesystems` form also shows whether an *administrative* announcement set has been defined. The *administrative* announcement set is the “working” version used to make changes. When the changes are complete, the administrator exchanges (*swaps*) the administrative announcement set with the currently active announcement set in order to hear the changes. When the administrator is satisfied with the changes, he or she copies the changes from the updated, active version to the previously active (now the new administrative) version. This last step ensures the system has two identical copies of the customized system announcements.

ANNOUNCEMENT CUSTOMIZATION PROCESS

How you customize announcements depends on the announcement and the global implication of changing its fragments:

- If the fragment or fragments you want to change are not used by any other announcement or only by announcements that you also want changed, you can simply re-record the fragments to be whatever you want using your touch-tone telephone.
- If the fragment or fragments you want to change are used by other announcements that you do *not* want to change, you can create and record new fragments to associate with just those announcements you want changed.

Either of these methods requires care, because fragments may be used by more than one system announcement. Study the tables in the appendixes before attempting to change system fragments, and use the `system : announcement : detail` form to verify which fragments make up a specific announcement before making changes.

You *cannot* make changes to the active announcement set in AUDIX R1 software; use the administrative copy to make changes. When you are satisfied with your changes (the customized announcements play correctly), you then make the administrative version the new active version so that users will hear the customized set of announcements. You should limit the number of administrative copies you create because keeping track of them may become confusing.

If you have more than one hard disk in your system, you may create the administrative filesystem on a different disk than the one containing the active announcements filesystem. Refer to the filesystem distribution guidelines in the *AUDIX System Description* manual (585-302-201) to determine the best drive on which to make your working copy (see Chapter 3, *AUDIX Software*). You may also back up either the active or administrative filesystem onto a removable cartridge disk if desired.

NOTE

If you plan to make extensive changes to the announcement sets, you may wish to create a backup copy, either on a hard disk or on a removable cartridge, *before* you begin modifying announcements.

2. Announcement Customization Procedures

The chapter describes the procedures for customizing system announcements. You can customize system announcements in the following ways:

- Re-record a fragment
- Delete a fragment
- Add a fragment

These procedures are described in this section.



If you decide to change a fragment recording or an announcement's composition, you must be extremely careful and precise. Failure to do so could jeopardize the integrity of your system. It is recommended that you do not attempt to modify any system announcements or fragments without the help of your AT&T representative (you may be charged for this service).

To Re-record a Fragment

The two announcements you will most likely want to change when you customize your AUDIX system are the default Call Answer greeting (the greeting someone hears when they are redirected to a subscriber's AUDIX mailbox) and the default Voice Mail greeting (the greeting subscribers hears when they call the AUDIX system directly). These announcement and fragment numbers are listed below.

- *Default Call Answer Greeting:* When someone calls a subscriber who is unavailable and the call is redirected to the AUDIX system, the caller hears the subscriber's personal greeting if one has been recorded. However, if a personal greeting was not recorded or is not active, the caller hears the default system greeting. This greeting begins with announcement 36, which contains only fragment number 43, "Your call is being answered by AUDIX". To customize this announcement (for example, with your company name), you would just re-record fragment number 43.
- *Default Voice Mail Greeting:* When a subscriber calls the AUDIX system directly, the subscriber is greeted by fragment number 287, *Welcome to AUDIX*, and fragment number 97, *For help at any time, press *H*. To customize this announcement (for example, with your company name), you would just re-record fragment number 287.

The procedure for re-recording a fragment is the same for any announcement, as described below:

1. Using Appendix A, *Standard Announcements*, note the fragment number(s) you want to change.
2. Using Appendix C, *Fragment/Announcement Cross-Reference*, verify that the fragment(s) are used only by announcements you expect to be affected by your changes. If too many announcements would be affected by changing a fragment, you may wish to record a *new* custom fragment instead of re-recording one (see the following *To Add a Fragment to an Announcement* section).

3. Log on to the AUDIX administration terminal.

NOTE

For details on using any of the following screen forms, refer to the *AUDIX Release 1 Version 8 Forms Reference* (585-305-209).

4. Use the `system : announcement : filesystems` form to determine if an administrative announcement version is mounted (available for use). If so, the name of the filesystem (such as **disk02.ans**) will be displayed in the `admin announcements` field. You can only make changes to an administrative (working) version of an announcement set.

If an active administrative announcement version is mounted *and* it is the version you want to change, go to the next step. If not, do the following:

- a. If the administrative version shown on the form is not the version you want to make changes to, but you know the name of the existing filesystem that you do want to modify, type the name of the correct administrative filesystem in the `admin announcements` field and press **F1** (CHANGE or RUN).
- b. If no administrative announcement set appears on the form, use the `filesystem : list` form to determine if an administrative version exists. If you find one (it may be on a different disk if your system has more than one hard disk drive), go back to the `system : announcement : filesystems` form and type the name of the administrative filesystem in the `admin announcements` field. Press **F1** (CHANGE or RUN).
- c. If an administrative version does not exist, create a new filesystem using the `filesystem : detail` form; this filesystem will contain the administrative version of your customized announcements (refer to the *Create a New Administrative Version* section in Chapter 3, *Post-Upgrade Procedures*, for the complete procedure). Go back to the `system : announcement : filesystems` form and type the name of the filesystem you just created in the `admin announcements` field. Press **F1** (CHANGE or RUN).

When you are sure that the correct administrative version is mounted, go to the next step.

5. You may want to make sure that the administrative version is identical to the active version before you make announcement changes. Using the `system : announcement : filesystems` form, tab to the `copy announcements (active to admin)` field. Type an **x** in the field and press **F1** (CHANGE or RUN). This copies the active version to the administrative version, resulting in two identical copies.
6. Use the `system : announcement : detail` form to verify that the announcement you plan to change is actually composed of the fragments you expect.
 - a. Move the cursor to the `filesystem name` field and type the name of the announcement filesystem to be accessed (in this case, the administrative version).
 - b. Move the cursor to the `announcement` field and type the number of the announcement containing the fragment(s) you wish to change. Press **F8** (ENTER).
 - c. Compare the list of fragments shown in the `composition` field with the notes you made from Steps 1 and 2. If there is a discrepancy, trust the information on the screen. (For example, a fragment may have been added to an announcement after the publication of this document.)

You should now have all the information you need to determine the impact of changing the fragment(s) in your target announcement.

7. Use the `subscriber : local` form to confirm that you have permission to access the system announcements (a `y` should appear in the `announcement control` field of your subscriber profile).
8. Using your touch-tone phone, log in to the AUDIX system.
 - a. At the activity menu, press **9**. (For security purposes, this option is not included in the voiced options you hear.) If you hear *“Entry not understood. Try again,”* you do not have announcement control permission.
 - b. When you hear *“To record names, press 4. To play names, press 5,”* press **1** to change fragments. (For security purposes, this option is not included in the voiced options you hear.)
 - c. Enter the fragment ID as prompted. For example, to change the default Call Answer greeting, you would press **4 3 #**.
 - d. Record the new fragment when prompted.

For example, your new fragment might be *“This is XYZ Company.”* You can use all the normal voice mail editing capabilities on your touch-tone phone to make sure the new fragment is exactly how you want it to sound.
 - e. When you are satisfied with the new fragment recording, press **#** to approve it.

For example, if you re-recorded the default Call Answer greeting, instead of saying, *“Your call is being answered by AUDIX,”* the system now says (in the administrator’s voice) *“This is XYZ Company.”*
9. At this point, only the administrative announcement version has this version of the re-recorded fragment. To update the currently active announcement set, go to the `system : announcement : filesystems` form and swap (exchange) the active and administrative announcement versions.
10. The announcement filesystem you modified is now the active announcement version. When you have tested it to your satisfaction, use the `system : announcement : filesystems` form again to copy the contents of the active version (your modified copy) to the administrative version (the version that was previously active) so that both versions are once again identical.

To Delete a Fragment from an Announcement

Some announcements can be modified by simply eliminating (deleting) an existing fragment from that specific announcement. For example, you could modify the default voice mail greeting (“*Welcome to AUDIX. For help at any time, press *H*”) to just say “*For help at any time, press *H*” by removing fragment number 287 (“*Welcome to AUDIX*”) from the list of fragments that compose the announcement (in this case, announcement number 240).

To delete a fragment from an announcement:

1. Using Appendix A, *Standard Announcements*, note the number of the announcement you want to change.
2. Use Steps 4 and 5 in the previous section to make sure the correct administrative announcement filesystem is mounted on the `system : announcement : filesystems` form.
3. Use the `system : announcement : detail` form to eliminate (delete) the fragment from the target announcement as follows:
 - a. Move the cursor to the `filesystem name` field and type the name of the administrative filesystem.
 - b. Move the cursor to the `announcement` field type the announcement number, in this case **240**.
 - c. Press **F8** (ENTER) to display and verify the fragment composition of the announcement. In this example, the fragment composition is `287,97`.
 - d. Change the composition line by spacing over or deleting the characters for the unwanted fragment(s). For example, delete the characters `287,.` Press **F1** (CHANGE or RUN).

Announcement number 240 is now composed of fragment number 97 only. Future callers will hear only the phrase, “*For help at any time, press *H*”.

4. At this point, only the administrative announcement version has this change to the announcement. To update the currently active announcement set, go to the `system : announcement : filesystems` form and swap (exchange) the active and administrative announcement versions.
5. The announcement filesystem you modified is now the active announcement version. When you have tested it to your satisfaction, use the `system : announcement : filesystems` form again to copy the contents of the active version (your modified copy) to the administrative version (the version that was previously active) so that both versions are once again identical.

To Add a Fragment to an Announcement

The previous examples dealt with modifications where the fragments being changed were not used by other announcements or where the fragment itself was left intact but was eliminated from just specific announcements. If you need to change the content of a fragment for some announcements but not others, you need to either substitute an existing fragment or create a new fragment for use by the announcements you want to change and leave the old fragment intact for use by existing announcements that you do not want changed. Be very careful if you do this.

For example, announcement number 61 and announcement number 78 are the only announcements that use fragment number 87, “*This call is experiencing difficulties.*” If you want to change this fragment for announcement number 61 but *not* for announcement number 78, you could create a new fragment to associate with announcement number 61 instead of fragment number 87; this would leave fragment number 87 and its association with announcement number 78 intact.

To add a fragment to an announcement:

1. Using Appendix A, *Standard Announcements*, verify that the announcement(s) you intend to change use only the fragments you expect.
2. Using Appendix B, *Standard Fragments*, locate an unused fragment number, indicated by the term “*not referenced.*” Fragment numbers up to 999 may be used (even though the table stops at number 978).

NOTE

Generally, using the highest numbered fragment available minimizes the chance that future software will reference that same fragment number. For example, start with fragment number 999 and work your way backwards through the table. Write down your customized fragments in Appendix B, *Standard Fragments*, or at the back of Appendix C, *Fragment/Announcement Cross-Reference*, in order to keep a written record of your changes.

3. Follow Steps 3 through 8 in the *To Re-record a Fragment* section.
4. When the AUDIX system prompts you to enter the fragment ID (Step 8c), enter an unused number. For example, you might press (9) (9) (9) (#).

5. Record the fragment when prompted.

For example, your new fragment might be “*This call is experiencing difficulties and cannot continue at this time.*” You can use all the normal voice mail editing capabilities on your touch-tone phone to make sure the new fragment is exactly how you want it to sound.

6. When you are satisfied with the new fragment recording, press (#) to approve it.
7. Use the `system : announcement : detail` form to add the new fragment to the appropriate announcement.
 - a. Move the cursor to the `filesystem` name field and type the name of the administrative filesystem.
 - b. Move the cursor to the `announcement` field type the announcement number, in this case **61**.
 - c. Press (F8) (ENTER) to display the fragment composition of the announcement. In this example, the fragment composition is:

- 87: This call is experiencing difficulties.
 - 236: Try again
 - 109: later.
 - 95: Please disconnect.
- d. Rewrite the line to reflect the new composition (in this case **999,236,109,95**) and press **F1** (CHANGE or RUN).

Announcement number 61 is now composed of the following fragments:

- 999: This call is experiencing difficulties and cannot continue at this time.
- 236: Try again
- 109: later.
- 95: Please disconnect.

Meanwhile, announcement number 78 still uses fragment number 87 as before.

8. At this point, only the administrative announcement version has this new version of the announcement and the new fragment. To update the currently active announcement set, go to the `system : announcement : filesystems` form and swap (exchange) the active and administrative announcement versions.
9. The announcement filesystem you modified is now the active announcement version. When you have tested it to your satisfaction, use the `system : announcement : filesystems` form again to copy the contents of the active version (your modified copy) to the administrative version (the version that was previously active) so that both versions are once again identical.

NOTE

Alternatively in this example, you could have created a new fragment number 999 with just the phrase “*and cannot continue at this time*” to use *in addition to* fragment number 87 instead of replacing it in announcement number 61. Either way, be careful if you make changes to announcements and fragments and be sure you have thoroughly researched the global ramifications of changes that you plan to make before you actually make them. Be sure to test your changes before copying them to the old (previously active) announcement set, because this will destroy the original version.

3. Post-Upgrade Procedures


The chapter describes the procedures for restoring your customized system announcements and/or fragments following an upgrade to R1V8 software.



Because of extensive changes to the announcement set in R1V8 software, you may not be able to simply copy the customized fragments from your old release into the new announcement set following an R1V8 upgrade. Follow the steps in this section to make sure your customized fragments and announcements are compatible with the new R1V8 system announcements.

Verify Customization Impact

If you upgraded to a new R1V8 announcement set, you may be able to copy some of your customized fragments into the new version. However, you must first determine that copying your existing customized fragments into the new version will not have an unintentional, adverse impact on the new announcement set. In addition, any other customization you did to announcements (such as adding, deleting, or replacing fragments) must be re-created in the new announcement set.



Because the default Call Answer and Voice Mail greetings are so often customized, fragment 43 (the default Call Answer greeting) and fragment 287 (the default Voice Mail greeting) are always the same from release to release. If these are the only fragments you customized, go on to the next section, *Create a New Administrative Version*, to begin restoring your customized fragments.

To verify the impact your customized announcements and/or fragments will have on the new announcement set, follow these steps:

1. Get the written record of your customized announcements and/or fragments. You need a list of any customized announcements (the announcement numbers and their composition) and your customized fragment numbers as well as the exact text of each customized announcement and/or fragment.
2. If you are upgrading from the R1V7 abbreviated announcement set, you can use Table 3-1, *R1V8 Announcement Composition*, as a quick-reference for checking which announcements changed in the R1V8 release. If any of the changed fragments or announcements will affect your customized announcements, make a note of them, then return to this checklist.

If you are upgrading from an earlier release of AUDIX software or from a verbose announcement set, additional announcements and/or fragments may have changed. Go on to the next step.

3. For each of your customized announcements/fragments, compare the wording of the *uncustomized* fragments and the *unaltered* composition of the announcements in your pre-R1V8 software release to the *uncustomized* R1V8 announcements and fragments using the appendixes in this guide.
 - If the wording and composition of the *uncustomized* R1V8 announcements and fragments is the same as in your earlier release, your customized announcements and/or fragments can be used in the R1V8 set without having an adverse effect on those announcements.
 - If the wording and composition of the *uncustomized* R1V8 announcements and/or fragments is *not* the same, you must judge whether or not your customized wording applies to the R1V8 set. If it does, your customized announcements and/or fragments can be used in the R1V8 set. If not, the affected fragment(s) must be re-recorded or the affected announcement(s) reconstructed.
 - For either of these cases, if the cross-reference tables indicate that a given fragment is used in *more* announcements in R1V8 than it was in the previous release, you need to make sure your customized wording works in the new additional announcements as well. Otherwise, you may need to re-record that fragment or reconstruct the affected customized announcement(s).
4. After you have checked your customized fragments and announcements against the text and composition of the new announcement set:
 - If you have determined that your customized announcements/fragments are compatible with the new R1V8 announcement set, you may copy your customized fragments into the new announcement set as described in the following sections.
 - If some of your customized fragments will affect new announcements that you *don't* want to change, you can copy each affected fragment into a new (unused) fragment number in the new version (described in the *Restore Customized Fragments* section), or you can record a new customized fragment. In either case, you will then have to customize the affected announcement(s) to use the new fragment number.
 - If you have determined that your customized announcements/fragments will *not* map correctly into the new R1V8 announcement set (for example, if the new software uses your customized fragment numbers as part of its regular announcement set, or if the text of the fragment has changed), you must re-create your customized announcements and/or fragments using the steps in Chapter 2, *Announcement Customization Procedures*.

Table 3-1. R1V8 Announcement Composition (*Page 1 of 2*)

Announcement Number	R1V7 Abbreviated Composition	R1V8 Standard Composition	R1V8 Traditional Composition
a1	f57	f57	f57, f171
a20	f41, f126, f8	f975, f18, f8	f975, f18, f8
a28	f323, f41, f126, f8, f235, f282	f323, f41, f126, f8, f975, f235, f282	f323, f41, f126, f8, f975, f235, f282
a29	f323, f486, f8, f235, f282	f323, f486, f8, f975, f235, f282	f323, f486, f8, f975, f235, f282
a47	f59	f59	f59, f171
a52	f323, f8, f235, f282	f323, f8, f975, f235, f282	f323, f8, f975, f235, f282
a116	f100, f151	f100, f96	f100, f96
a182	f64	f64	f64, f171
a230	f68	f68	f68, f171
a231	f69	f69	f69, f171
a232	f70	f70	f70, f171
a422	<blank>	f422	f422
a423	<blank>	f423	f423
a424	<blank>	f424	f424
a425	<blank>	f425	f425
a426	<blank>	f426	f426
a427	<blank>	f427	f427
a428	<blank>	f428	f428
a429	<blank>	f429	f429
a468	f473	f473	f473, f171
a508	f108, f13, f304, f339, f292, f497	f108, f167, f296, f339, f292, f497	f108, f13, f304, f339, f292, f497

(Continued)


TABLE 3-1. R1V8 Announcement Composition (*Page 2 of 2*)

Announcement Number	R1V7 Abbreviated Composition	R1V8 Standard Composition	R1V8 Traditional Composition
a517	f323, f486, f41, f126, f8, f163, f235, f282	f323, f486, f41, f126, f8, f163, f975, f235, f282	f323, f486, f41, f126, f8, f163, f975, f235, f282
a521	f323, f41, f126, f8, f163, f235, f282	f323, f41, f126, f8, f163, f975, f235, f282	f323, f41, f126, f8, f163, f975, f235, f282
a524	f323, f486, f8, f163, f235, f282	f323, f486, f8, f163, f975, f235, f282	f323, f486, f8, f163, f975, f235, f282
a528	f323, f8, f163, f235, f282	f323, f8, f163, f975, f235, f282	f323, f8, f163, f975, f235, f282
a546	f323, f486, f41, f126, f8, f235, f282	f323, f486, f41, f126, f8, f975, f235, f282	f323, f486, f41, f126, f8, f975, f235, f282
a727	f526	f526, f105	f526, f105
a748	f529, f527, f528, f235, f282	f529, f105, f527, f528, f235, f282	f529, f105, f527, f528, f235, f282
a750	f518, f13, f304, f292, f497, f572, f555, f282	f518, f13, f304, f292, f497, f555, f282	f518, f13, f304, f292, f497, f555, f282
a751	f529, f527, f528, f105, f282	f529, f105, f527, f528, f105, f282	f529, f105, f527, f528, f105, f282
a776	f572	<blank>	<blank>
a822	f622	<blank>	<blank>
a872	f464, f224, f572	f464, f224	f464, f224
a873	f465, f224, f572	f465, f224	f465, f224
a943	f734	<blank>	<blank>
a944	f735	<blank>	<blank>
a1058	f529, f527, f528, f235, f117, f282	f529, f105, f527, f528, f235, f117, f282	f529, f105, f527, f528, f235, f117, f282

Create a New Administrative Version

Before you copy your customized announcements into the new announcement set, you should delete any old copies of administrative announcement sets remaining from the previous software release, and create a new administrative (or “working”) version as described in this section.

1. Use the `list : volume names` form to display the names of the hard disks in your system (type **li vo** on the path line). Make a note of the `free space/size (blocks)` for each disk or print this screen.
2. Access the `filesystem : list` form by typing **fi li** on the path line (you need to display this form once for each disk volume if your system has more than one hard disk drive). Use this form to:
 - a. Locate the new active announcement set filesystem; it will have the mount point `/anp`. This filesystem is typically named `ana` (type `adat`) in R1V8 standard software, but the upgrade utility does not change the name or disk location of the active announcement filesystem from the previous release. For example, the new R1V8 announcement set might be named `anp` or `cust` if that was the name of the active announcement set prior to the upgrade. Make a note of the new filesystem’s name, size, and location, or print this screen.
 - b. Locate the *temporary* filesystem the upgrade utility created; it is named `temp` (type `adat`) and will be on the same disk as your new active version. This unmounted filesystem contains your customized announcement fragments.
 - c. Locate any existing administrative announcement sets that contain customized announcements from the previous software release and write down their names and locations (or print each screen). The old filesystems will all have a type of `adat` and will not be mounted (the `mount point` column will be blank).
 - d. Make sure enough space is available for the new administrative filesystem. Check the size of the new active announcement filesystem and compare it to the amount of free space remaining on the disk where you want the new copy to reside (see Step 1). The target volume must have sufficient space to hold another filesystem of the same block size as the original. (If you have more than one hard disk, you should place each announcement set on a separate volume to better protect against a loss of data should a hard disk problem occur.)
 - e. Press **CTRL-z** to exit the form.
3. Go to the `filesystem : detail` form by typing **fi de** on the path line. Press **RETURN**.



*Do **not** delete the new active announcement filesystem (indicated by mount point `/anp`) or the `temp adat` filesystem created by the upgrade utility!*

- a. In the `filesystem` field, type the name of an *old* administrative announcement filesystem from the previous software release (if one exists).
- b. Type **adat** in the `type` field.
- c. Press **F3** (DELETE) to delete the filesystem.
- d. Repeat Steps 3a through 3c to delete any additional *old* administrative announcement filesystems on your hard disk(s).

- e. When you have deleted all administrative announcement filesystems from the previous release, create an empty filesystem on the desired disk that will be your *new* administrative announcement filesystem. Type a descriptive name in the `filesystem` field (such as `disk02.cust`), type `adat`, with the same size as the new active announcement filesystem (see Step 2a). Press `(F2)` (ADD).
 - f. Press `(CTRL-z)` to exit the form.
4. Verify a new (empty) administrative filesystem of the correct size exists on the target volume using the `filesystem : list` form (type `fi li` on the path line).

Restore Customized Fragments

After you have determined which fragments you can safely copy using the steps in the *Verify Customization Impact* section, you can copy those customized fragments into your new administrative filesystem using the following procedure. If you altered the composition of any announcements (such as adding, deleting, or replacing fragments), you must also re-create those modifications in the new announcement set.

1. Go to the `system : announcement : filesystems` form by typing `sy an f` on the path line. Press `(RETURN)`.
 - a. Type the name of the administrative filesystem you just created in the `admin announcements` field (see the previous *Create a New Administrative Version* section). Press `(F1)` (CHANGE or RUN) to mount the new filesystem.
 - b. Tab to the `copy announcements (active to admin)` field and type `x`. Press `(F1)` (CHANGE or RUN). This copies the new R1V8 announcements into your administrative announcement set.
 - c. Press `(CTRL-z)` to exit the form.
2. Go to the `system : announcement : detail` form by typing `sy an de` on the path line. Press `(RETURN)`.
 - a. Type the name of the administrative announcement filesystem in the `filesystem` field (for example, `disk02.cust`).
 - b. Tab to the `fragment` field and type the number of the first fragment you want to customize in the new administrative announcement filesystem.
 - c. Tab to the `copy from filesystem` field and type the name of the *temporary* announcement filesystem created by the upgrade utility (for example, `disk02.temp`).
 - d. Tab to the `copy from fragment` field and type the number of the fragment you wish to copy into the new set. Typically this is the same fragment number as the previous one, but you may have to copy into a different fragment number if you noticed a conflict (refer to your notes from the *Verify Customization Impact* section).
 - e. Press `(F1)` (CHANGE or RUN).
 - f. Repeat this procedure for each customized fragment number that maps correctly into the new announcement set.

3. When you are finished copying fragments into the new announcement version, update the composition of your customized announcements if needed. For example, you may need to add, delete, or refer to new customized fragment numbers to have the new announcement set perform as the previous one did. To update the composition of the new announcements:
 - a. Blank out any fields *except* the `filesystem` name field on the `system : announcement : detail` form.
 - b. Move the cursor to the `announcement` field and type the number of the announcement whose composition you need to change. Press `(F8)` (ENTER).
 - c. Compare the list of fragments shown in the `composition` field with the notes you made in the *Verify Customization Impact* section. You may need to add, delete, or change the fragment numbers displayed in the field.
 - d. Make the appropriate changes to the entries in the `composition` field and press `(F1)` (CHANGE or RUN). Refer to the appropriate sections in Chapter 2, *Announcement Customization Procedures*, for details on adding or deleting fragments if needed.
4. When you are finished restoring your customized announcements and/or fragments, press `(CTRL-z)` to exit the `system : announcement : detail` form.
5. Go to the `system : announcement : filesystems` form by typing `sy an f` on the path line. Press `(RETURN)`.
 - a. Tab to `swap active` and `admin announcements` field and type `x`. Press `(F1)` (CHANGE or RUN). This makes the customized administrative announcement set the new active version.
 - b. Press `(CTRL-z)` to exit the form.
6. The announcement filesystem you modified is now the new active announcement version. When you have tested it to your satisfaction, use the `system : announcement : filesystems` form again to copy the contents of the active version (your modified copy) to the administrative version (the unaltered R1V8 version that was previously active) so both versions are once again identical.
7. When you are sure your modified announcement set is working correctly, go to the `filesystem : detail` form by typing `f d` on the path line. Press `(RETURN)`.
 - a. In the `filesystem` field, type the name of the temporary announcement filesystem (for example, `disk02.temp`.)
 - b. Type `adat` in the `type` field.
 - c. Press `(F3)` (DELETE) to delete the filesystem.
 - d. Press `(CTRL-z)` to exit the form.

A. Standard Announcements

This appendix lists all the announcements in the standard AUDIX system announcement set, as well as the associated fragments and their text.

Announcement	Fragment and Text	
a1	f57	accessed messages
a2	f73	You have
a3	f246	Message addressed to
a4	f336 f247	To review addressees, press star 1. To add to list,
a5	f334	When finished addressing, press pound.
a6	f160	message
a7	f18 f8	To forward with comment, press 2. To record a new message, press 4.
a8	f2	and
a9	f15	and is
a10	f16 f224	Enter announcement ID and pound sign.
a11	f131	To send to others not on your list,
a12	f595	including
a13	f88	Cannot use the guest password
a14	f272 f95	Contact administrator for help. Please disconnect.
a15	f29	Returned to checking status of outgoing messages.
a16	f31 f384	Date not understood. Please enter number of month, then two digits for day, and pound sign.
a17	f32	You must enter your extension to logon.
a18	f498 f224	Please enter a new list ID and pound sign.
a19	f35	Login incorrect.
a20	f975 f18 f8	To return to getting messages, press pound. To forward with comment, press 2. To record a new message, press 4.

Announcement	Fragment and Text
a21	f486 To reply to sender by voice mail, press 1. f8 To record a new message, press 4.
a22	f40 Time not understood. f383 Please enter hour, then two digits for minutes, then A for AM or P for PM, and pound sign.
a23	f20 Remote extension
a24	f21 To listen, press zero. f389 To delete, press star D. f388 To skip, press pound.
a25	f8 To record a new message, press 4.
a26	f91 At end.
a28	f323 You are responding to a piece of incoming mail. f41 To forward message with comment at beginning, press 2. f126 To forward message with comment at end, press 3. f8 To record a new message, press 4. f975 To return to getting messages, press pound. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a29	f323 You are responding to a piece of incoming mail. f486 To reply to sender by voice mail, press 1. f8 To record a new message, press 4. f975 To return to getting messages, press pound. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a30	f51 Entries deleted, please re-enter delivery time.
a31	f76 Deleted.
a32	f164 category.
a33	f44 is not available. To leave a message, wait for the tone.
a34	f42 The return address for this message is not a mailbox on this system.

Announcement	Fragment and Text	
a35	f56 f46	Thank you for leaving your message. To access your mailbox, press star R.
a36	f43	Your call is being answered by AUDIX.
a37	f60	Changed.
a38	f61	To modify status, press Y for yes or N for no.
a40	f65	contains
a41	f66	If correct, press pound. If not, press star D and re-enter time.
a43	f12	To re-record, press 1. After recording, press 1 again. To delete, press star D. To play back, press 2-3. To approve as is, press pound.
a44	f156 f56	Maximum length recorded. Thank you for leaving your message.
a45	f72	defaulted to
a46	f76	Deleted.
a47	f59	delivered messages
a48	f74	deleted.
a49	f77	Deleted.
a50	f98	Message not delivered due to transmission problems.
a51	f140	Entry already deleted. To delete more entries, press star 1.
a52	f323 f8 f975 f235 f282	You are responding to a piece of incoming mail. To record a new message, press 4. To return to getting messages, press pound. To restart at the activity menu, press star R. To transfer to another extension, press star T. To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a53	f79	Deleted.
a54	f252 f389 f388	To respond to this message, press 1. To delete, press star D. To skip, press pound.

Announcement	Fragment and Text
a55	f342 Electronic document communication
a56	f145 List has no entries.
a57	f83 entries.
a58	f85 Erased. f13 To record, press 1. After recording, press 1 again.
a59	f472 To approve, press pound. To record from here, press 1. f389 To delete, press star D.
a60	f86 extension
a61	f87 This call is experiencing difficulties. f236 Try again f109 later. f95 Please disconnect.
a62	f197 Cannot step back.
a63	f197 Cannot step back. f142 To listen to the header, press 3.
a64	f89 First message. f197 Cannot step back. f142 To listen to the header, press 3.
a65	f90 Enter fragment ID f224 and pound sign.
a66	f485 has
a67	f92 Nothing to advance.
a68	f491 You are getting your incoming messages. To listen to the message, press zero. To respond to the message, press 1. f376 To skip to the next header, press the pound sign. To listen to the header, rewind by pressing 2, then play by pressing 3. To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f377 To delete message, press star D.

Announcement	Fragment and Text	
a69	f232 f181	Recording stopped. Nothing to approve.
a70	f94	Good-bye.
a71	f99	Invalid announcement.
a72	f243	Rewound.
a73	f101	Invalid fragment.
a74	f103 f224	Invalid version, re-enter number and pound sign.
a75	f579	Password must be
a76	f44 f112	is not available. To leave a message, wait for the tone. Otherwise, for assistance, press zero now.
a77	f104	Message delivered, cannot listen to a delivered message.
a78	f87 f497	This call is experiencing difficulties. To review your message, press star 1.
a79	f106	Last list.
a80	f563 f224 f115	digit extension and pound sign. To transfer using names instead, press star A.
a81	f82	Please leave a message for
a82	f110	list
a83	f111 f224	Please enter list ID and pound sign.
a84	f49	No operator defined.
a85	f113	You already have a list
a86	f154	Cannot create new list, you have maximum lists allowed. To select lists to be deleted, press 5-1-2 and follow instructions.
a87	f155	Cannot create new list. Total number of members in all your lists equals maximum allowed.

Announcement	Fragment and Text
a88	f563 digit extension f224 and pound sign. f117 To reach the covering extension, press star zero. f115 To transfer using names instead, press star A.
a89	f118 Enter last name f224 and pound sign. f175 Please note only AUDIX subscribers can be specified by name.
a90	f128 To request another transfer, press star T. f129 or leave a message for
a91	f335 When finished, press pound.
a92	f122 List space nearly full. You may enter
a93	f123 new members.
a94	f121 When finished, approve list by pressing pound.
a95	f144 deleted, f130 because there were no entries.
a96	f3 No new remote subscribers can be addressed.
a97	f120 too large to include.
a98	f132 You can store your list as is by pressing star pound or add up to
a99	f277 To exit directory, press pound.
a100	f139 additional members,
a101	f288 You are in the names directory. To find a subscriber's extension, enter the last name followed by the pound sign. To enter the letter Q, press 7. For Z, press 9. To look up by extension instead press star A. f277 To exit directory, press pound. f105 To restart at the activity menu, press star R. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a102	f322 You are in the numbers directory. To find a subscriber's name enter the extension followed by the pound sign. To look up by name instead, press star A. f277 To exit directory, press pound. f105 To restart at the activity menu, press star R. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a103	f141 No more lists.
a104	f491 You are getting your incoming messages. To listen to the message, press zero. To respond to the message, press 1. f388 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H. f377 To delete message, press star D. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8.
a105	f231 cannot be found.
a106	f124 No more list space. f133 To continue reviewing, press 3. To delete an entry, press star D. If finished reviewing, press star pound.
a107	f116 List is full. f133 To continue reviewing, press 3. To delete an entry, press star D. If finished reviewing, press star pound.
a108	f114 To replace list, re-enter ID and pound sign. To create a new list, enter new list ID f224 and pound sign.
a109	f116 List is full. f349 To approve list as is, press pound. f241 To review list, press star 1.
a110	f134 You can store your list or delete members, but you cannot add members.
a111	f124 No more list space. f349 To approve list as is, press pound. f241 To review list, press star 1.

Announcement	Fragment and Text
a112	f121 When finished, approve list by pressing pound.
a114	f144 deleted,
a115	f107 Last member of list.
a116	f100 Invalid entry. f96 For help, press star H.
a117	f14 To make private, press 1. To make public, press 2.
a118	f343 Leave word calling
a119	f158 Transfer cannot be completed. f236 Try again f109 later. f95 Please disconnect.
a120	f563 digit extension f119 you wish to call f224 and pound sign. f115 To transfer using names instead, press star A. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a121	f153 Maximum length recorded. To re-record, press 2-1. To approve as is, press pound.
a122	f156 Maximum length recorded. f157 To approve as is, press pound.
a123	f344 Message Center Service
a124	f136 Line busy.
a126	f159 member.
a127	f150 members.
a128	f243 Rewound.
a129	f161 midnight.
a130	f168 messages.

Announcement	Fragment and Text
a131	f149 All circuits busy.
a132	f165 Returned to getting messages. f21 To listen, press zero. f255 To delete this message, press star D. f388 To skip, press pound.
a133	f166 At end. To play back, press 2-3.
a134	f167 To approve, press pound. To record from here, press 1. To play back, press 2-3.
a136	f170 Delivery scheduled
a137	f171 message summary.
a138	f63 new
a139	f172 You have new
a140	f201 noon.
a141	f105 To restart at the activity menu, press star R. f67 To create another list, f111 Please enter list ID f224 and pound sign.
a142	f105 To restart at the activity menu, press star R. f238 To review another list,
a143	f181 Nothing to approve. f95 Please disconnect.
a144	f53 Message deleted. No delivery will occur.
a145	f181 Nothing to approve.
a146	f203 No room in your mailbox for a recording. f62 Please delete unneeded messages.
a147	f203 No room in your mailbox for a recording. f62 Please delete unneeded messages.
a148	f203 No room in your mailbox for a recording. f62 Please delete unneeded messages.
a149	f215 No room to retain a copy. f62 Please delete unneeded messages.

Announcement	Fragment and Text
a150	f207 Message too long to add comment. To record a new message, press star R-1.
a151	f177 Cannot listen to a delivered message.
a152	f180 Nothing to approve.
a153	f178 No addressees identified.
a154	f181 Nothing to approve.
a155	f186 To record messages, press 1. To get messages, press 2. To check your outgoing messages, press 4.
a156	f182 Nothing to delete.
a157	f183 Nothing to delete.
a158	f184 Nothing to erase. f13 To record, press 1. After recording, press 1 again.
a159	f169 Administrative version not specified, please do so using administrator's terminal.
a160	f185 not found.
a161	f127 Returned to previous activity. f96 For help, press star H.
a163	f188 Passwords do not match. Please re-enter new password f224 and pound sign.
a164	f189 You have no mailbox. f272 Contact administrator for help.
a165	f190 Message delivered, you cannot change it now.
a166	f191 No more messages.
a167	f192 No messages.
a168	f194 No new messages.
a169	f195 No messages.
a170	f196 You have no personal greeting.
a171	f199 Nothing to rewind.

Announcement	Fragment and Text
a172	f200 No time entered. Nothing to delete. f22 To deliver now, press pound. To schedule delivery time enter hour, minutes, A or P, and pound sign.
a173	f389 To delete, press star D. f388 To skip, press pound.
a174	f202 not valid.
a175	f208 is not a public list.
a176	f209 Cannot modify another subscriber's list.
a177	f6 Enter machine voice ID. f224 and pound sign.
a178	f173 Please enter new password f224 and pound sign.
a179	f213 Re-enter password f224 and pound sign.
a180	f468 To continue playing, press 3.
a181	f10 That is not a valid machine voice ID.
a182	f64 old messages
a183	f217 others
a184	f11 You are recording machine names. f6 Enter machine voice ID. f224 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a185	f218 deleted.
a186	f219 owned by
a187	f220 Enter password f224 and pound sign.
a189	f226 private

Announcement	Fragment and Text
a190	f227 public
a191	f242 Returned to the
a192	f228 Record at the tone.
a193	f230 seconds to record.
a194	f236 Try again
a195	f19 To review from beginning, press star 1. If finished, press star pound.
a196	f142 To listen to the header, press 3. f143 To step back again, press 2.
a197	f142 To listen to the header, press 3.
a198	f146 To continue, press pound. f143 To step back again, press 2.
a199	f1 Someone is changing your greeting. Please try again later.
a200	f146 To continue, press pound.
a201	f486 To reply to sender by voice mail, press 1. f18 To forward with comment, press 2. f8 To record a new message, press 4.
a202	f234 To respond or forward, press 1. f389 To delete, press star D. f388 To skip, press pound.
a203	f256 At beginning. To re-record, press 1. To play back, press 2-3.
a204	f570 Recorded name too long
a206	f244 Rewound to previous message. f142 To listen to the header, press 3.
a208	f98 Message not delivered due to transmission problems.
a209	f387 Message not delivered because recipient not found.
a211	f245 Please return call.
a212	f248 scheduled
a213	f249 To change delivery time, press star D

Announcement	Fragment and Text
a214	f250 To change delivery time, press star D.
a215	f22 To deliver now, press pound. To schedule delivery time enter hour, minutes, A or P, and pound sign.
a216	f253 Please enter month, day f224 and pound sign.
a217	f138 You are listening to machine names. f6 Enter machine voice ID. f224 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a220	f294 To add entries, press 1.
a221	f23 To record messages, press 1. To get messages, press 2. To administer your greeting, press 3.
a222	f243 Rewound. f142 To listen to the header, press 3. f143 To step back again, press 2.
a223	f21 To listen, press zero. f24 To delete, press star D. f388 To skip, press pound.
a224	f270 subscriber ID
a226	f26 To record names, press 4. To play names, press 5. To record machine names, press 6. To play machine names, press 7.
a227	f96 For help, press star H. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X. f274 Please make entry soon, or be disconnected.
a228	f275 Cannot get your messages now, due to multiple logins to your mailbox. f95 Please disconnect.

Announcement	Fragment and Text	
a229	f7	Cannot listen to an undeliverable message.
a230	f68	undeliverable messages
a231	f69	undelivered messages
a232	f70	unopened messages
a233	f278 f224	Please enter extension and pound sign.
a234	f279 f280	For active version, press 1. For administrative version, press 2.
a235	f345	Voice mail
a236	f283	Your mailbox is more than
a237	f284	percent full. Please delete unneeded messages or greetings.
a238	f276	Time requested has passed, please re-schedule delivery.
a240	f287 f97	Welcome to AUDIX. For help at any time, press star H.
a241	f179	Warning, if you do not supply an addressee list, message will be deleted immediately.
a248	f293	Nothing to play back.
a249	f34	Electronic Text
a251	f499	When finished recording, press pound to approve or 1 to edit your message.
a252	f389 f388	To delete, press star D. To skip, press pound.
a253	f388	To skip, press pound.
a254	f33 f388	To delete, press star D. To skip, press pound.
a255	f37 f187 f464 f135 f349	Extension entered not followed by pound and not added to the list. Enter extension and pound sign. To approve list as is, press pound.

Announcement	Fragment and Text
a256	f38 Name entered not followed by pound f187 and not added to the list. f465 Enter last name f135 and pound sign. f349 To approve list as is, press pound.
a257	f474 To listen, press zero. To change or send again, press 1. f389 To delete, press star D. f388 To skip, press pound.
a258	f30 To change, press 1. f24 To delete, press star D. f388 To skip, press pound.
a259	f386 Cannot change a delivered message.
a260	f300 A. M.
a261	f301 P. M.
a262	f387 Message not delivered because recipient not found.
a270	f310 January
a271	f311 February
a272	f312 March
a273	f313 April
a274	f314 May
a275	f315 June
a276	f316 July
a277	f317 August
a278	f318 September
a279	f319 October
a280	f320 November
a281	f321 December
a282	f258 Message to

Announcement	Fragment and Text	
a283	f259	scheduled for
a284	f260	scheduled for
a285	f261	rescheduled for
a287	f262	received
a289	f264	Message not delivered because mailbox was full.
a290	f265	Message not delivered because their mailboxes were full.
a291	f266	was undeliverable
a292	f466	created
a301	f5	To record personal greeting, press 1. To listen to personal greeting, press zero. To select which greeting to use, press star pound.
a302	f50	Call
a303	f78	delivered at
a304	f281	Message from
a305	f54	was only partially recorded due to a system problem.
a306	f55	The message was delivered at
a307	f216	originally
a308	f216 f260	originally scheduled for
a309	f214	Approved.
a310	f93	You have no personal greeting. System greeting used.
a311	f331	Personal greeting used.
a312	f332	System greeting used.
a313	f257	To use personal greeting, press Y. To use system greeting, press N.
a314	f45	is busy. To leave a message, wait for the tone.
a315	f102	That is not a valid extension.

Announcement	Fragment and Text	
a316	f267 f224	Please enter extension and pound sign.
a317	f267 f224 f237	Please enter extension and pound sign. Or press star R.
a318	f193	No name recorded.
a319	f267 f224 f237	Please enter extension and pound sign. Or press star R.
a320	f152	Leave Word Calling from
a322	f176 f224	Enter fragment ID and pound sign.
a323	f477	Press 1 to select
a324	f478	2 to select
a325	f479	3 to select
a326	f480	4 to select
a327	f481	5 to select
a328	f482	Press pound to select
a329	f483 f225	or enter more characters and pound sign.
a330	f484 f225	Enter more characters followed by the pound sign; if you just completed entering the last name, enter the first name. and pound sign.
a340	f25 f498 f224	List-ID not followed by pound. Please enter a new list ID and pound sign.
a341	f125 f111 f224	Must be six or fewer numerals. Please enter list ID and pound sign.
a342	f464 f135	Enter extension and pound sign.

Announcement	Fragment and Text	
a343	f465 f135	Enter last name and pound sign.
a344	f37 f469 f224 f471	Extension entered not followed by pound Enter owner's extension and pound sign. If it's your list, press pound.
a345	f38 f470 f224 f471	Name entered not followed by pound Enter owner's last name and pound sign. If it's your list, press pound.
a346	f469 f224 f471	Enter owner's extension and pound sign. If it's your list, press pound.
a347	f470 f224 f471	Enter owner's last name and pound sign. If it's your list, press pound.
a348	f229	You will have up to
a349	f240 f296	To skip, press pound. To listen, press zero. To delete, press star D.
a350	f75	To skip, press pound. To delete, press star D.
a351	f494	private.
a352	f495	public.
a353	f147	Review completed.
a354	f492	Owner erased.
a355	f295	To re-enter list, press star L.
a356	f198	Partial name deleted.
a357	f469 f224 f471	Enter owner's extension and pound sign. If it's your list, press pound.
a358	f470 f224 f471	Enter owner's last name and pound sign. If it's your list, press pound.

Announcement	Fragment and Text
a359	f496 Filed.
a360	f350 Sunday
a361	f351 Monday
a362	f352 Tuesday
a363	f353 Wednesday
a364	f354 Thursday
a365	f355 Friday
a366	f356 Saturday
a367	f18 To forward with comment, press 2.
a368	f258 Message to
a369	f84 entry.
a390	f390 oh
a391	f391 one
a392	f392 two
a393	f393 three
a394	f394 four
a395	f395 five
a396	f396 six
a397	f397 seven
a398	f398 eight
a399	f399 nine
a400	f400 ten
a401	f401 eleven
a402	f402 twelve
a403	f403 thirteen

Announcement	Fragment and Text
a404	f404 fourteen
a405	f405 fifteen
a406	f406 sixteen
a407	f407 seventeen
a408	f408 eighteen
a409	f409 nineteen
a410	f410 twenty
a411	f411 twenty-one
a412	f412 twenty-two
a413	f413 twenty-three
a414	f414 twenty-four
a415	f415 twenty-five
a416	f416 twenty-six
a417	f417 twenty-seven
a418	f418 twenty-eight
a419	f419 twenty-nine
a420	f420 thirty
a421	f421 thirty-one
a422	f422 thirty-two
a423	f423 thirty-three
a424	f424 thirty-four
a425	f425 thirty-five
a426	f426 thirty-six
a427	f427 thirty-seven
a428	f428 thirty-eight

Announcement	Fragment and Text
a429	f429 thirty-nine
a430	f430 forty
a431	f431 forty-one
a432	f432 forty-two
a433	f433 forty-three
a434	f434 forty-four
a435	f435 forty-five
a436	f436 forty-six
a437	f437 forty-seven
a438	f438 forty-eight
a439	f439 forty-nine
a440	f440 fifty
a441	f441 fifty-one
a442	f442 fifty-two
a443	f443 fifty-three
a444	f444 fifty-four
a445	f445 fifty-five
a446	f446 fifty-six
a447	f447 fifty-seven
a448	f448 fifty-eight
a449	f449 fifty-nine
a450	f450 sixty
a451	f451 seventy
a452	f452 eighty
a453	f453 ninety

Announcement	Fragment and Text
a454	f454 hundred
a455	f455 thousand
a456	f456 million
a457	f457 billion
a462	f462 pound
a463	f463 star
a464	f234 To respond or forward, press 1.
a466	f27 To attach original, press Y for yes or N for no.
a467	f475 To file a copy, press Y for yes or N for no.
a468	f473 filed messages
a469	f474 To listen, press zero. To change or send again, press 1. f388 To skip, press pound.
a471	f472 To approve, press pound. To record from here, press 1. f468 To continue playing, press 3.
a472	f47 Call from
a500	f299 You are administering your greeting. f5 To record personal greeting, press 1. To listen to personal greeting, press zero. To select which greeting to use, press star pound. f39 To delete, press star D. To stop playback, press 3. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a501	f263 You are recording a subscriber name. f13 To record, press 1. After recording, press 1 again.

Announcement	Fragment and Text
a502	f299 You are administering your greeting. f36 To record a personal greeting, press 1. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a503	f346 You are recording a machine name. f13 To record, press 1. After recording, press 1 again.
a504	f302 You are recording announcement fragments. Enter fragment ID followed by pound sign. Refer to admin manual for correct ID. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a505	f71 To leave a message, wait for the tone.
a506	f303 You are recording names. Enter extension and pound sign. f224 f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a507	f263 You are recording a subscriber name. f573 To record from here, press 1. f583 After you finish recording, press 1 again. f304 To play back message, press 2-3. To delete your message, press star D. To approve your message, press pound. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f497 To review your message, press star 1.

Announcement	Fragment and Text
a508	f108 You are recording a message. f167 To approve, press pound. To record from here, press 1. To playback, press 2-3. f296 To delete message, press star D. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f497 To review your message, press star 1.
a509	f346 You are recording a machine name. f13 To record, press 1. After recording, press 1 again. f304 To play back message, press 2-3. To delete your message, press star D. To approve your message, press pound. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f497 To review your message, press star 1.
a510	f108 You are recording a message. f13 To record, press 1. After recording, press 1 again. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8.
a511	f380 Please wait.
a512	f305 You are at the activity menu. f23 To record messages, press 1. To get messages, press 2. To administer your greeting, press 3. f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a513	f13 To record, press 1. After recording, press 1 again.
a515	f486 To reply to sender by voice mail, press 1. f18 To forward with comment, press 2. f8 To record a new message, press 4. f163 To call sender, press zero.

Announcement	Fragment and Text
a516	f278 Please enter extension f224 and pound sign. f330 Or enter just the pound sign if it's your phone.
a517	f323 You are responding to a piece of incoming mail. f486 To reply to sender by voice mail, press 1. f41 To forward message with comment at beginning, press 2. f126 To forward message with comment at end, press 3. f8 To record a new message, press 4. f163 To call sender, press zero. f975 To return to getting messages, press pound. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a518	f278 Please enter extension f224 and pound sign.
a519	f18 To forward with comment, press 2. f8 To record a new message, press 4. f163 To call sender, press zero.
a520	f233 Previous login incorrect. Please re-enter extension f224 and pound sign. f330 Or enter just the pound sign if it's your phone.
a521	f323 You are responding to a piece of incoming mail. f41 To forward message with comment at beginning, press 2. f126 To forward message with comment at end, press 3. f8 To record a new message, press 4. f163 To call sender, press zero. f975 To return to getting messages, press pound. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a522	f486 To reply to sender by voice mail, press 1. f8 To record a new message, press 4. f163 To call sender, press zero.

Announcement	Fragment and Text
a523	f233 Previous login incorrect. Please re-enter extension f224 and pound sign.
a524	f323 You are responding to a piece of incoming mail. f486 To reply to sender by voice mail, press 1. f8 To record a new message, press 4. f163 To call sender, press zero. f975 To return to getting messages, press pound. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a525	f220 Enter password f224 and pound sign.
a526	f8 To record a new message, press 4. f163 To call sender, press zero.
a527	f370 These are entries in your list. f333 To add entries to the list or to change status of list, press 1. f371 To rewind to current entry, press 2. To rewind to previous entries, press 2 as many times as necessary. To continue playback of list, press 3. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f372 To skip to next entry, press pound. To delete current entry, press star D. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a528	f323 You are responding to a piece of incoming mail. f8 To record a new message, press 4. f163 To call sender, press zero. f975 To return to getting messages, press pound. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a529	f118 Enter last name f224 and pound sign. f175 Please note only AUDIX subscribers can be specified by name. f117 To reach the covering extension, press star zero. f251 To transfer using extension instead, press star A.
a530	f306 You are changing your password. f210 Please enter a new password f224 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a531	f118 Enter last name f224 and pound sign. f251 To transfer using extension instead, press star A.
a532	f306 You are changing your password. f212 Please enter password again for confirmation. To delete the password you just entered, press star D. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a533	f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a534	f308 You are playing announcement fragments. f254 To play the active version, press 1. f338 To play the administrative version, press 2. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a536	f308 You are playing announcement fragments. f222 Enter fragment ID and pound sign. Refer to administration manual for correct ID. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a537	f46 To access your mailbox, press star R. f117 To reach the covering extension, press star zero. f291 To transfer to another extension, press star T.
a538	f307 You are playing announcements. f254 To play the active version, press 1. f338 To play the administrative version, press 2. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a539	f45 is busy. To leave a message, wait for the tone. f112 Otherwise, for assistance, press zero now.
a540	f307 You are playing announcements. f221 Enter announcement ID and pound sign. Refer to administration manual for correct ID. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a543	f46 To access your mailbox, press star R. f291 To transfer to another extension, press star T.

Announcement	Fragment and Text
a544	f309 You are playing names. f223 Please enter extension f224 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a545	f563 digit extension f119 you wish to call f224 and pound sign. f115 To transfer using names instead, press star A. f105 To restart at the activity menu, press star R. f117 To reach the covering extension, press star zero. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a546	f323 You are responding to a piece of incoming mail. f486 To reply to sender by voice mail, press 1. f41 To forward message with comment at beginning, press 2. f126 To forward message with comment at end, press 3. f8 To record a new message, press 4. f975 To return to getting messages, press pound. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a547	f493 You are requesting a transfer. f118 Enter last name f119 you wish to call f224 and pound sign. f290 If you wish to specify a non-AUDIX subscriber, first change to extension addressing by pressing star A. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a548	<p>f375 You are getting your incoming messages. To listen to the message, press zero. To respond to the message, press 1.</p> <p>f376 To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.</p> <p>f577 To hold the message in its current category, press star star H</p> <p>f339 To replay the last few seconds, press 5. To advance a few seconds, press 6.</p> <p>f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8.</p> <p>f377 To delete message, press star D.</p>
a549	<p>f493 You are requesting a transfer.</p> <p>f118 Enter last name</p> <p>f119 you wish to call</p> <p>f224 and pound sign.</p> <p>f290 If you wish to specify a non-AUDIX subscriber, first change to extension addressing by pressing star A.</p> <p>f105 To restart at the activity menu, press star R.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a550	<p>f378 You are checking the status of your outgoing messages.</p> <p>f376 To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.</p> <p>f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8.</p> <p>f379 To delete status information, press star D.</p>
a551	<p>f128 To request another transfer, press star T.</p>
a552	<p>f378 You are checking the status of your outgoing messages.</p> <p>f381 To listen to the message, press zero. To re-record message before delivery, press 1.</p> <p>f376 To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.</p> <p>f339 To replay the last few seconds, press 5. To advance a few seconds, press 6.</p> <p>f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8.</p> <p>f377 To delete message, press star D.</p>

Announcement	Fragment and Text
a560	f382 You are scheduling your message for delivery. f488 To specify immediate delivery, press pound. Otherwise f340 Enter the hour, one through twelve, then two digits for the minutes, then A for AM or P for PM, and the pound sign.
a562	f382 You are scheduling your message for delivery. f341 Enter the month, one through twelve, then two digits for the day of the month, then the pound sign. f487 To delete time, press star D. To default rest of the delivery time, press pound.
a566	f385 To approve delivery time, press pound. To modify delivery time, press star D and listen for further instructions.
a568	f324 You are selecting which greeting will be played to callers. If you want your personal greeting to be played, press Y for yes. If you press N for no, the system greeting will be used. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a572	f326 You are doing system administration. To record names, press 4. To play names, press 5. To record a machine name, press 6. To play a machine name, press 7. To record fragments, press 1. To play fragments, press 2. To play announcements, press 3. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a574	f327 You are creating a mailing list. f285 To add a member, enter extension f224 and pound sign. f328 To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move onto the next step, press pound. f58 For name addressing, press star A. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a575	f561 You are addressing your message. f285 To add a member, enter extension f224 and pound sign. f328 To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move onto the next step, press pound. f58 For name addressing, press star A.
a576	f347 You are adding a list. f111 Please enter list ID f224 and pound sign. f366 To specify a different owner by extension, press star D. f363 To approve the list you are creating, press pound.
a578	f359 You are changing the status of your list. To modify status, press Y for yes or N for no. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a580	f360 You are scanning mailing lists. To review list members, press zero. To rewind to previous list, press 2. To continue scanning lists, press 3. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f361 To skip to next list, press pound. To delete list, press star D. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a582	f368 You are entering the number for a new list. Please enter a number up to six digits long and pound sign. f224 f369 To replace an existing list, enter that list's number, and pound sign. f224 f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a584	f370 These are entries in your list. f294 To add entries, press 1. f371 To rewind to current entry, press 2. To rewind to previous entries, press 2 as many times as necessary. To continue playback of list, press 3. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f372 To skip to next entry, press pound. To delete current entry, press star D. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a586	f46 To access your mailbox, press star R.

Announcement	Fragment and Text
a588	f358 You are identifying a list as private or public. f14 To make private, press 1. To make public, press 2. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a590	f374 You are choosing whether to file this message. To file a copy, press Y for yes. To send without filing a copy, press N for no. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a592	f373 You are choosing whether to attach a copy of original message to your reply. To include the original, press Y for yes. To send only your reply, press N for no. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a594	f378 You are checking the status of your outgoing messages. f474 To listen, press zero. To change or send again, press 1. f376 To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f377 To delete message, press star D.

Announcement	Fragment and Text
a596	<p>f327 You are creating a mailing list.</p> <p>f286 To add a member, enter last name</p> <p>f224 and pound sign.</p> <p>f328 To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move onto the next step, press pound.</p> <p>f148 For extension addressing, press star A.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a597	<p>f561 You are addressing your message.</p> <p>f286 To add a member, enter last name</p> <p>f224 and pound sign.</p> <p>f328 To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move onto the next step, press pound.</p> <p>f148 For extension addressing, press star A.</p>
a598	<p>f347 You are adding a list.</p> <p>f362 If you own the list, press pound. If someone else owns the list</p> <p>f364 enter owner's extension</p> <p>f224 and pound sign.</p> <p>f298 To specify owner by name, press star A.</p>
a600	<p>f347 You are adding a list.</p> <p>f362 If you own the list, press pound. If someone else owns the list</p> <p>f365 enter owner's name</p> <p>f224 and pound sign.</p> <p>f297 To specify owner by extension, press star A.</p>
a602	<p>f357 You are choosing between subscribers whose names match your entry. To indicate no subscribers match, delete your entry by pressing star D. To change to extension addressing and delete your entry, press star A.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

Announcement	Fragment and Text
a604	f483 or enter more characters f225 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a606	f327 You are creating a mailing list. f329 You have not yet entered enough characters to identify a specific subscriber. To enter the letter Q, press 7; for Z press 9. f484 Enter more characters followed by the pound sign; if you just completed entering the last name, enter the first name. f225 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a608	f347 You are adding a list. f111 Please enter list ID f224 and pound sign. f367 To specify a different owner by name, press star D. f363 To approve the list you are creating, press pound.
a610	f348 You are specifying a mailing list to review. f362 If you own the list, press pound. If someone else owns the list f364 enter owner's extension f224 and pound sign. f298 To specify owner by name, press star A. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a612	<p>f348 You are specifying a mailing list to review. f362 If you own the list, press pound. If someone else owns the list f365 enter owner's name f224 and pound sign. f297 To specify owner by extension, press star A. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a614	<p>f348 You are specifying a mailing list to review. f111 Please enter list ID f224 and pound sign. f366 To specify a different owner by extension, press star D. f363 To approve the list you are creating, press pound. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a616	<p>f348 You are specifying a mailing list to review. f111 Please enter list ID f224 and pound sign. f367 To specify a different owner by name, press star D. f363 To approve the list you are creating, press pound. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

Announcement	Fragment and Text
a618	f348 You are specifying a mailing list to review. f329 You have not yet entered enough characters to identify a specific subscriber. To enter the letter Q, press 7; for Z press 9. f484 Enter more characters followed by the pound sign; if you just completed entering the last name, enter the first name. f225 and pound sign. f148 For extension addressing, press star A. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a700	f501 To record messages, press 1. To get messages, press 2. To administer attendant menu, press 3.
a701	f305 You are at the activity menu. f501 To record messages, press 1. To get messages, press 2. To administer attendant menu, press 3. f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R. f291 To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a702	f502 To record attendant menu, press 1. To listen to attendant menu, press zero. f105 To restart at the activity menu, press star R.
a703	f503 You are administering your attendant menu. f502 To record attendant menu, press 1. To listen to attendant menu, press zero. f550 To rewind your attendant menu, press 2. To delete it, press star D. To stop playback of your attendant menu, press 3. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a704	f503 You are administering your attendant menu. f502 To record attendant menu, press 1. To listen to attendant menu, press zero. f550 To rewind your attendant menu, press two. To delete it, press star D. To stop playback of your attendant menu, press three. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a705	f504 Transferring to an operator,
a706	f505 You have selected an invalid option.
a707	f506 Menu approved and activated.
a708	f547 Good-bye
a709	f43 Your call is being answered by AUDIX. f507 The person you called is not available. To leave a message, use touch tones to re-enter the number you called. f239 followed by the pound sign. f555 To access your mailbox, press star R.
a710	f559 A name cannot be recorded until the size of the names file system is increased.
a711	f510 Number
a712	f511 If you do not have a touch tone phone, f236 Try again f109 later. f514 otherwise f274 Please make entry soon, or be disconnected.
a713	f274 Please make entry soon, or be disconnected.
a714	f507 The person you called is not available. To leave a message, use touch tones to re-enter the number you called.
a715	f515 To be transferred to an operator,
a716	f512 Your call is being transferred to an operator.

Announcement	Fragment and Text
a717	f513 Begin your message by saying the name and telephone number of the person you are calling. Someone will listen to the start of your message, and then forward the complete message to the person you called.
a718	f516 To leave a message that will be delivered as soon as possible,
a719	f500 This is AUDIX.
a720	f519 You are not authorized for outcalling.
a721	f520 Your outcalling number,
a722	f521 turned on
a723	f522 turned off
a724	f523 for
a725	f524 to
a726	f525 any time
a727	f526 subject to administrator restrictions f105 To restart at the activity menu, press star R.
a728	f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3.
a729	f528 To turn on, press y. To turn off, press n.
a730	f530 Outcalling
a731	f533 Too many digits.
a732	f534 Your outcalling number is
a733	f531 Enter outcalling number f224 and pound sign.

Announcement	Fragment and Text
a734	<p>f532 To change your outcalling phone number, press 1 and enter the number to be called followed by the pound sign. Anything you enter will be interpreted as a part of the called number. No global commands such as star H will be accepted at this time.</p> <p>f557 In most cases, entering a star or pound as the first digit will result in the star or pound being outpulsed. A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row.</p> <p>f560 If you are programming a number to call a pager that requires a pound sign termination, press y to hear further help. Otherwise, press n to return to outcalling administration.</p>
a735	<p>f535 For outcalling any time, press 1. For outcalling during prime time, press 2. To specify your times, press 3. For system outcalling schedule, press 4.</p>
a736	<p>f536 You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator.</p> <p>f535 For outcalling any time, press 1. For outcalling during prime time, press 2. To specify your times, press 3. For system outcalling schedule, press 4.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a737	<p>f536 You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator.</p> <p>f545 To delete own time, press star D.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a738	<p>f508 Attendant Service not available, try again later.</p> <p>f95 Please disconnect.</p>
a739	<p>f537 Enter the starting hour, minutes, A or P, and pound sign.</p>

Announcement	Fragment and Text
a740	f538 Enter the ending hour, minutes, A or P, and pound sign.
a741	f509 System not administered for outcalling.
a742	f539 The system allows outcalls from
a743	f540 and from
a744	f541 Up to
a745	f542 digits may be used.
a746	<p>f517 You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.</p> <p>f46 To access your mailbox, press star R.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a747	<p>f518 You are creating a voice message which will be delivered to the person specified in your message as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion.</p> <p>f13 To record, press 1. After recording, press 1 again.</p> <p>f304 To play back message, press 2-3. To delete your message, press star D. To approve your message, press pound.</p> <p>f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8.</p> <p>f497 To review your message, press star 1.</p> <p>f46 To access your mailbox, press star R.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a748	<p>f529 You are changing your outcalling options.</p> <p>f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3.</p> <p>f528 To turn on, press y. To turn off, press n.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

Announcement	Fragment and Text
a749	f517 You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign. f555 To access your mailbox, press star R. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a750	f518 You are creating a voice message which will be delivered to the person specified in your message as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion. f13 To record, press 1. After recording, press 1 again. f304 To play back message, press 2-3. To delete your message, press star D. To approve your message, press pound. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f497 To review your message, press star 1. f555 To access your mailbox, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a751	f529 You are changing your outcalling options. f105 To restart at the activity menu, press star R. f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3. f528 To turn on, press y. To turn off, press n. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a752	f546 pause
a753	f536 You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator. f535 For outcalling any time, press 1. For outcalling during prime time, press 2. To specify your times, press 3. For system outcalling schedule, press 4. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a754	f536 You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator. f545 To delete own time, press star D. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a755	f100 Invalid entry.
a756	f172 You have new f168 messages. f551 To access your messages, f278 Please enter extension f224 and pound sign. f543 To avoid further notification of these messages, press star pound. <BEEP>
a757	f95 Please disconnect.
a758	f549 You are administering your attendant menu. To create attendant menu, press 1. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a759	f549 You are administering your attendant menu. To create attendant menu, press 1. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a760	f548 You have no attendant menu.
a761	f556 To exit, press star pound now.
a762	f552 is not authorized to receive messages.
a763	f553 You may enter another number

Announcement	Fragment and Text
a764	f589 For pagers requiring a pound sign termination, start your number with a double pound sign. This will result in a single pound being outpulsed at the end of the digit string. Then, a star or pound in the next position will be interpreted as part of the outcalling number. f590 A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row.
a765	f511 If you do not have a touch tone phone, f380 Please wait.
a766	f544 Outcalling specified for
a767	f558 subject to administrator restrictions.
a768	f562 Enter the
a769	f493 You are requesting a transfer. f562 Enter the
a770	f564 There is no room in the mailbox to leave a message. f236 Try again f109 later.
a771	f565 Outcall canceled for new messages currently in mailbox.
a772	f566 You are responding to an outcall notifying you of new messages. f551 To access your messages, f278 Please enter extension f224 and pound sign. f543 To avoid further notification of these messages, press star pound. <BEEP> f567 Either logging in or pressing star pound will result in the outcall being canceled for the new messages currently in your mailbox. If additional new messages arrive, another outcall will be scheduled."
a773	f569 To modify, press one. If finished, press star pound.
a774	f571 Non-existent subscriber
a775	f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f117 To reach the covering extension, press star zero. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a777	f573 To record from here, press 1.
a778	f574 Private
a779	f575 Cannot forward a private message
a780	f576 Recipients can forward this message
a781	f580 Cannot attach a private message
a782	f211 to fifteen digits
a783	f306 You are changing your password. f210 Please enter a new password f224 and pound sign. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a784	f306 You are changing your password. f212 Please enter password again for confirmation. To delete the password you just entered, press star D. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a785	f581 Press N now
a786	f582 AUDIX passwords must now be at least
a787	f81 digits.
a788	f591 To change your outcalling phone number, press 1. To hear further instructions on programming a pager, press y. To return to outcalling administration, press n.
a789	f584 Message not delivered because special feature denied on recipients machine.
a790	f585 Zero
a791	f586 To skip, press pound.

Announcement	Fragment and Text
a792	f587 You are reviewing a list. f586 To skip, press pound. f371 To rewind to current entry, press 2. To rewind to previous entries, press 2 as many times as necessary. To continue playback of list, press 3. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a793	f588 or more digits.
a794	f592 AUDIX passwords must now be
a795	f593 Please choose a new password of
a800	f600 New Broadcast messages.
a801	f601 Priority
a802	f602 other
a803	f603 You also have
a804	f604 As you use AUDIX your name will be included in system announcements that you and other people will hear. Press 1, and at the tone, please speak your name. After speaking your name, press 1 again.
a806	f606 To re-record your name, press 1. To approve, press pound.
a807	f607 Name cannot be saved at this time. Please continue
a808	f608 At the tone, please speak your name. After speaking your name, press 1.
a809	f609 No room to save Broadcast message so it will be retained in the new message category.
a810	f610 You are recording your name. After you record your name, you can access other AUDIX features. As you use AUDIX your name will be included in system announcements that you and other people will hear. Press 1 and at the tone, please speak your first and last name as you would like others to hear it. After speaking your name, press 1 again.

Announcement	Fragment and Text
a811	f611 You are recording your name. To record your name, press 1. After recording, press 1 again. To play back name, press 2-3. To approve, press pound.
a812	f612 To make private, press 1.
a813	f613 To make priority, press 2.
a814	f614 To make broadcast, press 8.
a815	f615 To make a login announcement, press 9.
a816	f616 To exit options menu, press pound.
a817	f617 To remove private status, press 1.
a818	f618 To remove priority status, press 2.
a819	f619 To remove broadcast status, press 8.
a820	f620 To remove login announcement status, press 9.
a821	f621 Private.
a823	f623 Broadcast.
a824	f624 Login announcement.
a825	f625 To activate message waiting notification, press 1.
a826	f626 To specify expiration date, press 2.
a827	f627 To approve broadcast options, press pound.
a828	f628 To deactivate message waiting notification, press 1.
a829	f629 Please enter month, day, and pound sign.
a830	f630 To change expiration date from
a831	f631 Message waiting notification activated.
a832	f632 Expiration date will be
a833	f633 To make non-interruptible, press 1.
a834	f634 To approve login announcement options, press pound.
a835	f635 To remove non-interruptible status, press 1.

Announcement	Fragment and Text
a836	f636 Login announcement will be non-interruptible.
a837	f637 Invalid date.
a838	f638 is prior to delivery date, please re-schedule.
a839	f639 Message cannot be both broadcast and priority.
a840	f640 Message cannot be both a login announcement and priority.
a841	f641 Message cannot be both a login announcement and private.
a842	f642 Message cannot be both broadcast and a login announcement
a843	f643 You are choosing options for this message. There are no options currently set.
a844	f644 You are choosing options for this message. With the current settings,
a845	f645 Private messages cannot be forwarded by the recipients.
a846	f646 A priority message will be delivered before other messages and will be flagged for special attention in the recipient's mailbox.
a847	f647 the message will be private.
a848	f648 the message will be priority.
a849	f649 the message will be broadcast.
a850	f650 the message will be a login announcement.
a851	f651 the message will be private and priority.
a852	f652 A broadcast message is delivered to every subscriber on this machine. You may also address a broadcast message to subscribers on other machines.
a853	f653 For broadcast options, press star M.
a854	f654 the message will be broadcast and private.
a855	f655 A login announcement will be played each time any subscriber logs onto this machine. You may also address a login message to subscribers on other machines.
a856	f656 For login announcement options, press star M.
a857	f657 You are choosing options for this broadcast message.

Announcement	Fragment and Text
a858	f658 Message waiting notification is currently not active.
a859	f659 Message waiting notification will alert all local subscribers of this message. This option should be used sparingly, for it can impact system performance.
a860	f660 Expiration date specifies the last day this broadcast message will be available to subscribers. The expiration date does not apply to a broadcast message already received by a subscriber and saved in their mailbox. The default expiration date is the second day after the scheduled delivery date.
a861	f661 To approve these options, press pound.
a862	f662 Message waiting notification is active.
a863	f663 Message waiting notification is not active and this message has an expiration date of.
a864	f664 Message waiting notification is active and this message has an expiration date of.
a865	f665 You are choosing options for this login announcement.
a866	f666 With the current settings, this login announcement will be non-interruptible.
a867	f667 With the current settings, this login announcement will be interruptible.
a868	f668 With the current settings, this login announcement will be non-interruptible and the login announcement has an expiration date of.
a869	f669 With the current settings, this login announcement will be interruptible and the login announcement has an expiration date of.
a870	f670 Non-interruptible status forces each subscriber to listen to the entire login announcement every time they log onto this machine.
a871	f671 Expiration date specifies the last day this login announcement will be available to subscribers. The default expiration date is the second day after the scheduled delivery date.
a872	f464 Enter extension f224 and pound sign.
a873	f465 Enter last name f224 and pound sign.

Announcement	Fragment and Text
a874	f674 Due to sending restrictions, you cannot send messages to
a878	f678 is past the expiration date. Please reschedule.
a879	f679 is not available. Sorry, you cannot leave a message now because this user's mailbox is full.
a880	f680 is busy. Sorry, you cannot leave a message now because this user's mailbox is full.
a881	f681 Sorry, cannot leave a message now because this user's mailbox is full.
a882	f682 Broadcast message from
a883	f683 Broadcaster has deleted this broadcast message.
a884	f684 Private, broadcast message from
a885	f685 Private, priority message from
a886	f686 Private message from
a887	f687 Undeliverable message notification received
a888	f688 An undeliverable message was returned to your outgoing mailbox. To access your outgoing mailbox, press star R 4.
a889	f689 Expiration time is
a890	f690 Priority message from
a891	f691 Login announcement from
a892	f692 Broadcast message deleted.
a893	f693 Broadcast message to all local subscribers
a894	f694 Private, broadcast message to all local subscribers
a895	f695 Private, priority message to
a896	f696 Private message to
a897	f697 Login announcement to all local subscribers
a898	f698 Priority message to
a899	f699 Message not delivered because another login announcement is active.
a900	f700 To administer mailing lists, press 1. To administer personal directory, press 2.

Announcement	Fragment and Text
a901	f701 To change your password, press 4.
a902	f702 To record your name, press 5.
a903	f703 You are at subscriber administration.
a904	f704 To create lists, press 1. To scan lists, press 2. To review and modify lists, press 3.
a905	f705 Directory contains
a906	f706 To add entries, press 1. To review all entries, press 2. To review a specific entry, press 3.
a907	f707 If finished, press star pound.
a908	f708 If finished adding entries, press pound.
a909	f709 Enter alias for
a910	f710 Enter next name and pound sign.
a911	f711 Alias
a912	f712 defined for
a913	f713 Enter next extension and pound sign.
a914	f714 Directory has no entries.
a915	f715 Cannot add new entries because your directory is full.
a916	f716 Alias must be ten or fewer numerals.
a917	f717 Alias already defined.
a918	f718 Name entered not followed by pound and not added to the directory.
a919	f719 Extension entered not followed by pound and not added to the directory.
a920	f720 Alias entered not followed by pound and not added to the directory.
a921	f721 Directory is full.
a922	f722 was not added to your personal directory.
a923	f723 You are administering your personal directory.
a924	f724 Personal directory review completed.

Announcement	Fragment and Text
a925	f725 You are adding entries to your personal directory.
a926	f726 You are reviewing all entries in your personal directory. f372 To skip to next entry, press pound. To delete current entry, press star D. f852 To rewind to the current entry, press two. To rewind to previous entries, press two as many times as necessary.
a927	f727 Enter alias and pound sign.
a928	f728 deleted.
a929	f729 You are reviewing a specific entry in your personal directory. To delete the current entry, press star D. To review another entry, enter the alias followed by the pound sign.
a930	f730 Message not delivered because the broadcast mailbox was not defined.
a931	f232 Recording stopped.
a932	f305 You are at the activity menu. f23 To record messages, press 1. To get messages, press 2. To administer your greeting, press 3. f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R. f291 To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a933	f305 You are at the activity menu. f731 To record messages, press 1. To get messages, press 2. f48 To check your outgoing messages, press 4. To administer , press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a934	f305 You are at the activity menu. f731 To record messages, press 1. To get messages, press 2. f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R. f291 To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a935	f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a936	f305 You are at the activity menu. f23 To record messages, press 1. To get messages, press 2. To administer your greeting, press 3. f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R. f291 To transfer to another extension, press star T. f117 To reach the covering extension, press star zero. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a937	f736 You are recording your name. As you use AUDIX, your name will be included in system announcements that you and other people will hear.
a938	f555 To access your mailbox, press star R. f117 To reach the covering extension, press star zero. f291 To transfer to another extension, press star T. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a939	f555 To access your mailbox, press star R. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a940	f555 To access your mailbox, press star R. f291 To transfer to another extension, press star T. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a946	f737 Login announcement will be interruptible.
a947	f738 Message not delivered due to sending restrictions.
a948	f739 Message sent to all local subscribers.
a949	f740 Private message sent to all local subscribers.
a950	f741 Private, priority message sent to
a951	f742 Private message sent to
a952	f743 Priority message sent to
a953	f744 For all calls,...
a954	f745 active.
a956	f747 For internal calls,...
a957	f748 For external calls,...
a958	f749 For busy calls,...
a959	f750 For no answer calls,...
a960	f751 For out-of-hours calls,...
a961	f752 To listen to a greeting, press zero. To create, change or delete a greeting, press 1. To scan all your greetings, press 2. To activate a greeting, press 3. To administer call types, press 4. If finished, press pound.
a962	f753 Enter greeting number.
a963	f754 Greeting
a964	f755 not recorded.
a965	f756 To listen to greeting
a966	f757 To re-record, press 1.
a967	f758 To delete, press star D.

Announcement	Fragment and Text
a968	f759 To review status, press 2.
a969	f760 press zero.
a971	f762 press 2.
a973	f764 To use this greeting for all calls, press zero. For internal calls, press 1. For external calls, press 2.
a974	f765 recorded, but not active
a975	f766 To use this greeting for all calls, press 1.
a976	f767 To use this greeting for all calls, press zero. For busy calls, press 1. For no answer calls, press 2.
a977	f768 approved.
a978	f769 Nothing to approve.
a979	f770 recorded and active
a980	f771 approved and active
a981	f772 again
a982	f773 To activate for out-of-hours calls, press 3.
a983	f774 If you have addressed this message and wish to deliver it immediately, press star star pound.
a984	f775 To record messages, press one. To get messages, press two. To administer personal greetings, press 3.
a985	f776 the system greeting
a986	f777 Cannot listen to system greeting.
a987	f778 Cannot modify system greeting.
a988	f779 No greetings recorded.
a989	f780 Personal greetings review completed.
a990	f781 To skip to the next greeting, press the pound sign.

Announcement	Fragment and Text
a991	f782 To activate a greeting, enter greeting number. To deactivate a greeting, activate a different greeting in its place.
a992	f783 To activate another greeting, enter greeting number. To deactivate a greeting, activate a different greeting in its place.
a993	f784 To activate system greeting, enter zero.
a994	f785 Same greeting used for all calls.
a995	f786 To identify calls as internal and external, press 1.
a996	f787 To identify calls as busy and no answer, press 2.
a997	f788 To identify calls as out-of-hours, press 3.
a998	f789 Otherwise, press 4.
a999	f790 Calls identified as internal and external.
a1000	f791 Calls identified as busy and no answer.
a1001	f792 Calls identified as out-of-hours.
a1002	f793 Calls not identified as out-of-hours.
a1003	f794 To change identification to busy and no answer, press 2.
a1004	f795 To change identification to internal and external, press 1.
a1005	f796 To remove out-of-hours identification, press 4.
a1006	f797 To use same greeting for all calls, press 5.
a1007	f798 Prime time is
a1008	f799 Enter last name f224 and pound sign.
a1009	f800 You are specifying the expiration date.
a1010	f384 Please enter number of month, then two digits for day, and pound sign.
a1011	f215 No room to retain a copy.
a1012	f801 To respond to this notification, press one. To delete, press star D. To skip, press pound.
a1013	f802 Cannot send a message to the broadcast mailbox.

Announcement	Fragment and Text
a1015	f804 not defined.
a1016	f805 For internal...
a1017	f806 For external...
a1018	f807 For busy...
a1019	f808 For no answer...
a1020	f809 internal
a1021	f810 external
a1022	f811 busy
a1023	f812 no answer
a1024	f813 and out-of-hours
a1025	f814 calls.
a1026	f815 You are administering your personal greetings.
a1027	f816 You are listening to a personal greeting.
a1028	f817 You are recording a personal greeting.
a1029	f818 You have just recorded
a1030	f819 You are scanning your personal greetings.
a1031	f820 You are selecting which greeting to activate.
a1032	f821 You are administering call types.
a1034	f325 You are administering your lists. To create a mailing list, press 1. To play a summary of all your lists, press 2. To review a particular list, press 3.
a1035	f822 As you use AUDIX, your name will be included in system announcements that you and other people will hear. At the tone, please speak your name. After speaking your name, press one.
a1036	f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8.
a1037	f823 for all calls

Announcement	Fragment and Text
a1038	f305 You are at the activity menu. f501 To record messages, press 1. To get messages, press 2. To administer attendant menu, press 3. f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a1039	f825 for internal
a1040	f826 for external
a1041	f827 for busy
a1042	f828 for no answer
a1043	f829 for out-of-hours
a1044	f830 You must approve your recording.
a1045	f831 To exit the expiration date options, press star pound.
a1046	f372 To skip to next entry, press pound. To delete current entry, press star D.
a1047	f832 Please enter extension and pound sign.
a1048	f224 and pound sign.
a1049	f305 You are at the activity menu. f731 To record messages, press 1. To get messages, press 2. f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R. f291 To transfer to another extension, press star T. f117 To reach the covering extension, press star zero. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a1050	<p>f305 You are at the activity menu.</p> <p>f501 To record messages, press 1. To get messages, press 2. To administer attendant menu, press 3.</p> <p>f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a1051	<p>f305 You are at the activity menu.</p> <p>f775 To record messages, press 1. To get messages, press 2. To administer personal greetings, press 3.</p> <p>f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a1052	<p>f305 You are at the activity menu.</p> <p>f775 To record messages, press 1. To get messages, press 2. To administer personal greetings, press 3.</p> <p>f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

Announcement	Fragment and Text
a1053	f305 You are at the activity menu. f775 To record messages, press 1. To get messages, press 2. To administer personal greetings, press 3. f48 To check your outgoing messages, press 4. To administer mailing lists, personal directory, password or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R. f291 To transfer to another extension, press star T. f117 To reach the covering extension, press star zero. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a1054	f833 To delete current entry, press star D. f58 For name addressing, press star A.
a1055	f833 To delete current entry, press star D. f148 For extension addressing, press star A.
a1056	f835 for all new messages
a1057	f836 only for new priority messages
a1058	f529 You are changing your outcalling options. f105 To restart at the activity menu, press star R. f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3. f528 To turn on, press y. To turn off, press n. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f117 To reach the covering extension, press star zero. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a1059	f837 To turn on Outcalling for all new messages, press 1. To turn on outcalling only for new priority messages, press 2.
a1060	f838 You are selecting which messages will receive outcalls.
a1061	f839 To rewind to the previous greeting, press 2.
a1062	f840 Option
a1063	f841 not defined

Announcement	Fragment and Text
a1064	f842 Announcement not recorded. Try again later. f95 Please disconnect.
a1065	f843 To scan headers and messages, press 1. To scan headers only, press 2. To scan messages only, press 3.
a1066	f844 End of message.
a1067	f845 Next message.
a1068	f846 You are selecting an option for Automatic Message Scan. f843 To scan headers and messages, press 1. To scan headers only, press 2. To scan messages only, press 3.
a1069	f847 You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to or forward the message, press one. f849 To skip to the next message, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f377 To delete message, press star D.
a1070	f848 You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to the message, press one. f849 To skip to the next message, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f377 To delete message, press star D.
a1071	f850 Broadcast and Login Message services are not available.
a1072	f165 Returned to getting messages. f21 To listen, press zero. f389 To delete, press star D. f851 To skip, press pound.
a1073	f333 To add entries to the list or to change status of list, press 1.
a1074	f853 Messages skipped, retained as new.
a1075	f854 seconds to finish recording.

Announcement	Fragment and Text	
a1076	f856	This is a recorded message from
a1077	f861	AMIS
a1078	f562 f855 f224	Enter the remote AMIS mailbox ID and pound sign.
a1079	f867 f855 f868 f833	You are entering the remote AMIS mailbox ID Mailbox ID must be less than or equal to 16 digits. To delete current entry, press star D.
a1080	f862	It could not be delivered because the recipient appears to be a wrong number.
a1081	f863	It could not be delivered after multiple attempts to deliver the message.
a1082	f864	Automated call, please press 1 to disconnect.
a1083	f865	Your number was dialed by mistake. We're sorry for this inconvenience. To prevent this from recurring, this call has been reported as a misdialled call.
a1084	f857	from
a1085	f21 f594	To listen, press zero. To delete, press star D. <BEEP>
a1086	f858 f389	To replay, press zero. To delete, press star D.
a1087	f76 f95	Deleted. Please disconnect.
a1088	f21 f389 f80	To listen, press zero. To delete, press star D. To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a1089	f859	Mailbox ID not followed by pound.
a1090	f860	Mailbox ID not valid.
a1091	f866	AMIS casual subscribers cannot be added to your list.

Announcement	Fragment and Text
a1092	f561 You are addressing your message. f285 To add a member, enter extension f224 and pound sign. f869 If the extension entered belongs to a casual AMIS subscriber, you will be prompted for a mailbox ID. f868 Mailbox ID must be less than or equal to 16 digits. f328 To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move onto the next step, press pound. f58 For name addressing, press star A.
a1093	f375 You are getting your incoming messages. To listen to the message, press zero. To respond to the message, press 1. f388 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f377 To delete message, press star D.
a1094	f378 You are checking the status of your outgoing messages. f388 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f379 To delete status information, press star D.
a1095	f378 You are checking the status of your outgoing messages. f381 To listen to the message, press zero. To re-record message before delivery, press 1. f388 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f377 To delete message, press star D.

Announcement	Fragment and Text
a1096	f378 You are checking the status of your outgoing messages. f474 To listen, press zero. To change or send again, press 1. f388 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f377 To delete message, press star D.
a1097	f847 You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to or forward the message, press one. f851 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f377 To delete message, press star D.
a1098	f848 You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to the message, press 1. f851 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. softer, press 7. faster, press 9. slower, press 8. f377 To delete message, press star D.
a1099	f158 Transfer cannot be completed.
a1100	f870 The following message was restored.
a1101	f871 No message to restore.
a1102	f872 To undelete last deleted message, press star star U.
a1103	f937 Sorry you are having difficulty. Please get help and try again later. f547 Good-bye

Announcement	Fragment and Text
a1104	f124 No more list space. f970 To continue reviewing, press 3. To delete an entry, press star D. If finished reviewing, press pound.
a1105	f914 not filed
a1106	f915 No options menu available.
a1107	f916 To send message, press pound or enter a delivery option. To hear a list of options, press zero.
a1108	f917 To schedule delivery, press 3.
a1109	f918 To re-schedule delivery, press 3.
a1110	f919 To file a copy, press 4.
a1111	f920 To not file a copy, press 4.
a1112	f921 To make private, press 1. To send, press pound.
a1113	f922 To access the Delivery Options Menu, press "#" after recording your message.
a1114	f923 Press "#" to approve your message and access the Delivery Options Menu.
a1115	f86 extension
a1116	f924 seconds
a1117	f925 minutes
a1118	f926 <error sound>
a1119	f928 New Messages
a1120	f936 Partial entry deleted
a1121	f617 To remove private status, press 1. f971 To send, press pound.
a1122	f913 If finished, press pound.
a1123	f976 Name

Announcement	Fragment and Text
a1124	f329 You have not yet entered enough characters to identify a specific subscriber. To enter the letter Q, press 7; for Z press 9. f484 Enter more characters followed by the pound sign; if you just completed entering the last name, enter the first name. f224 and pound sign. f758 To delete, press star D.
a1125	f605 Not private.
a1126	f622 Not Priority.
a1127	f977 Not Broadcast.
a1128	f978 Not Login Announcement.
a1129	f971 To send, press pound.
a1130	f975 To return to getting messages, press pound. f8 To record a new message, press 4.
a1140	f900 zeroth.
a1141	f938 first.
a1142	f939 second.
a1143	f940 third.
a1144	f941 fourth.
a1145	f942 fifth.
a1146	f943 sixth.
a1147	f944 seventh.
a1148	f945 eighth.
a1149	f946 ninth.
a1150	f947 tenth.
a1151	f948 eleventh.
a1152	f949 twelfth.
a1153	f950 thirteenth.
a1154	f951 fourteenth.

Announcement	Fragment and Text	
a1155	f952	fifteenth.
a1156	f953	sixteenth.
a1157	f954	seventeenth.
a1158	f955	eighteenth.
a1159	f956	nineteenth.
a1160	f957	twentieth.
a1161	f958	twenty-first.
a1162	f959	twenty-second.
a1163	f960	twenty-third.
a1164	f961	twenty-fourth.
a1165	f962	twenty-fifth.
a1166	f963	twenty-sixth.
a1167	f964	twenty-seventh.
a1168	f965	twenty-eighth.
a1169	f966	twenty-ninth.
a1170	f967	thirtieth.
a1171	f968	thirty-first.
a1172	f901	fortieth.
a1173	f902	fiftieth.
a1174	f903	sixtieth.
a1175	f904	seventieth.
a1176	f905	eightieth.
a1177	f906	ninetieth.
a1178	f907	hundredth.
a1179	f908	thousandth.
a1180	f909	millionth.

Announcement	Fragment and Text	
a1181	f910	billionth.
a1182	f291	To transfer to another extension, press star T.
a1183	f972	To reach the covering extension, press zero.
a1184	f973	If you are finished, please hang up.
a1185	f974	The return address for this message is not a valid extension.
a1186	f975 f291 f96	To return to getting messages, press pound. To transfer to another extension, press star T. For help, press star H.

B. Standard Fragments

This appendix lists the text for all the fragments in the standard AUDIX system announcement set.

Fragment	Text
f1	Someone is changing your greeting. Please try again later.
f2	and
f3	No new remote subscribers can be addressed.
f4	at end.
f5	To record personal greeting, press 1. To listen to personal greeting, press zero. To select which greeting to use, press star pound.
f6	Enter machine voice ID.
f7	Cannot listen to an undeliverable message.
f8	To record a new message, press 4.
f9	You may now record new messages.
f10	That is not a valid machine voice ID.
f11	You are recording machine names.
f12	To re-record, press 1. After recording, press 1 again. To delete, press star D. To play back, press 2-3. To approve as is, press pound.
f13	To record, press 1. After recording, press 1 again.
f14	To make private, press 1. To make public, press 2.
f15	and is
f16	Enter announcement ID
f17	at beginning.
f18	To forward with comment, press 2.
f19	To review from beginning, press star 1. If finished, press star pound.
f20	Remote extension
f21	To listen, press zero.
f22	To deliver now, press pound. To schedule delivery time enter hour, minutes, A or P, and pound sign.

Fragment	Text
f23	To record messages, press 1. To get messages, press 2. To administer your greeting, press 3.
f24	To delete, press star D.
f25	List-ID not followed by pound.
f26	To record names, press 4. To play names, press 5. To record machine names, press 6. To play machine names, press 7.
f27	To attach original, press Y for yes or N for no.
f28	Returned to incoming messages.
f29	Returned to checking status of outgoing messages.
f30	To change, press 1.
f31	Date not understood.
f32	You must enter your extension to logon.
f33	To delete, press star D.
f34	Electronic Text
f35	Login incorrect.
f36	To record a personal greeting, press 1.
f37	Extension entered not followed by pound.
f38	Name entered not followed by pound.
f39	To delete, press star D. To stop playback, press 3.
f40	Time not understood.
f41	To forward message with comment at beginning, press 2.
f42	The return address for this message is not a mailbox on this system.
f43	Your call is being answered by AUDIX.
f44	is not available. To leave a message, wait for the tone.
f45	is busy. To leave a message, wait for the tone.
f46	To access your mailbox, press star R.

B-4 Standard Fragments

Fragment	Text
f47	Call from
f48	To check your outgoing messages, press 4. To administer mailing lists, personal directory, password, or account name, press 5. To change outcalling information, press 6. To scan incoming messages automatically, press 7. To re-logon, press star star R.
f49	No operator defined.
f50	Call
f51	Entries deleted, please re-enter delivery time.
f52	Delivery is canceled and
f53	Message deleted, no delivery will occur.
f54	was only partially recorded due to a system problem.
f55	The message was delivered at
f56	Thank you for leaving your message.
f57	accessed messages
f58	For name addressing, press star A.
f59	delivered messages
f60	Changed.
f61	To modify status, press Y for yes or N for no.
f62	Please delete unneeded messages.
f63	new
f64	old messages
f65	contains
f66	If correct, press pound. If not, press star D and re-enter time.
f67	To create another list,
f68	undeliverable messages
f69	undelivered messages
f70	unopened messages

Fragment	Text
f71	To leave a message, wait for the tone.
f72	defaulted to
f73	You have
f74	deleted.
f75	To skip, press pound. To delete, press star D.
f76	Deleted.
f77	Deleted.
f78	delivered at
f79	Deleted.
f80	To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
f81	digits.
f82	Please leave a message for
f83	entries.
f84	entry.
f85	Erased.
f86	extension
f87	This call is experiencing difficulties.
f88	Cannot use the guest password
f89	First message.
f90	Enter fragment ID
f91	At end.
f92	Nothing to advance.
f93	You have no personal greeting. System greeting used.
f94	Good-bye.

Fragment	Text
f95	Please disconnect.
f96	For help, press star H.
f97	For help at any time, press star H.
f98	Message not delivered due to transmission problems.
f99	Invalid announcement.
f100	Invalid entry.
f101	Invalid fragment.
f102	That is not a valid extension.
f103	Invalid version, re-enter number
f104	Message delivered. Cannot listen to a delivered message.
f105	To restart at the activity menu, press star R.
f106	Last list.
f107	Last member of list.
f108	You are recording a message.
f109	later.
f110	list
f111	Please enter list ID
f112	Otherwise, for assistance, press zero now.
f113	You already have a list
f114	To replace list, re-enter ID and pound sign. To create a new list, enter new list ID
f115	To transfer using names instead, press star A.
f116	List is full.
f117	To reach the covering extension, press star zero.
f118	Enter last name
f119	you wish to call

Fragment	Text
f120	too large to include.
f121	When finished, approve list by pressing pound.
f122	List space nearly full. You may enter
f123	new members.
f124	No more list space.
f125	Must be six or fewer numerals.
f126	To forward message with comment at end, press 3.
f127	Returned to previous activity.
f128	To request another transfer, press star T.
f129	or leave a message for
f130	because there were no entries.
f131	To send to others not on your list,
f132	You can store your list as is by pressing star pound or add up to
f133	To continue reviewing, press 3. To delete an entry, press star D. If finished reviewing, press star pound.
f134	You can store your list or delete members, but you cannot add members.
f135	and pound sign.
f136	Line busy.
f137	or approve entire list by pressing star pound.
f138	You are listening to machine names.
f139	additional members,
f140	Entry already deleted. To delete more entries, press star 1.
f141	No more lists.
f142	To listen to the header, press 3.
f143	To step back again, press 2.

Fragment	Text
f144	deleted,
f145	List has no entries.
f146	To continue, press pound.
f147	Review completed.
f148	For extension addressing, press star A.
f149	All circuits busy.
f150	members.
f151	<i>not referenced</i>
f152	Leave Word Calling from
f153	Maximum length recorded. To re-record, press 2-1. To approve as is, press pound.
f154	Cannot create new list. You have maximum lists allowed. To select lists to be deleted, press 5-1-2 and follow instructions.
f155	Cannot create new list. Total number of members in all your lists equals maximum allowed.
f156	Maximum length recorded.
f157	To approve as is, press pound.
f158	Transfer cannot be completed.
f159	member.
f160	message
f161	midnight.
f162	To record personal greeting, press one. To listen to personal greeting, press zero. To select which greeting to use, press star pound.
f163	To call sender, press zero.
f164	category.
f165	Returned to getting messages.
f166	At end. To play back, press 2-3.

Fragment	Text
f167	To approve, press pound. To record from here, press 1. To play back, press 2-3.
f168	messages.
f169	Administrative version not specified. Please do so using administrator's terminal.
f170	Delivery scheduled
f171	message summary.
f172	You have new
f173	Please enter new password
f174	Please make next entry.
f175	Please note only AUDIX subscribers can be specified by name.
f176	Enter fragment ID
f177	Cannot listen to a delivered message.
f178	No addressees identified.
f179	Warning! If you do not supply an addressee list, message will be deleted immediately.
f180	Nothing to approve.
f181	Nothing to approve.
f182	Nothing to delete.
f183	Nothing to delete.
f184	Nothing to erase.
f185	not found.
f186	To record messages, press 1. To get messages, press 2. To check your outgoing messages, press 4.
f187	and not added to the list.
f188	Passwords do not match. Please re-enter new password
f189	You have no mailbox.
f190	Message delivered. You cannot change it now.

Fragment	Text
f191	No more messages.
f192	No messages.
f193	No name recorded.
f194	No new messages.
f195	No messages.
f196	You have no personal greeting.
f197	Cannot step back.
f198	Partial name deleted.
f199	Nothing to rewind.
f200	No time entered, nothing to delete.
f201	noon.
f202	not valid.
f203	No room in your mailbox for a recording.
f204	another message.
f205	your response.
f206	comment.
f207	Message too long to add comment. To record a new message, press star R-1.
f208	is not a public list.
f209	Cannot modify another subscriber's list.
f210	Please enter a new password
f211	to fifteen digits
f212	Please enter password again for confirmation. To delete the password you just entered, press star D.
f213	Re-enter password
f214	Approved.
f215	No room to retain a copy.

Fragment	Text
f216	originally
f217	others
f218	deleted.
f219	owned by
f220	Enter password
f221	Enter announcement ID and pound sign. Refer to administration manual for correct ID.
f222	Enter fragment ID and pound sign. Refer to administration manual for correct ID.
f223	Please enter extension
f224	and pound sign.
f225	and pound sign.
f226	private
f227	public
f228	Record at the tone.
f229	You will have up to
f230	seconds to record.
f231	cannot be found.
f232	Recording stopped.
f233	Previous login incorrect. Please re-enter extension
f234	To respond or forward, press 1.
f235	To restart at the activity menu, press star R. To transfer to another extension, press star T.
f236	Try again
f237	Or press star R.
f238	To review another list,
f239	followed by the pound sign.

Fragment	Text
f240	To skip, press pound. To listen, press zero.
f241	To review list, press star 1.
f242	Returned to the
f243	Rewound.
f244	Rewound to previous message.
f245	Please return call.
f246	Message addressed to
f247	To add to list,
f248	scheduled
f249	To change delivery time, press star D
f250	To change delivery time, press star D.
f251	To transfer using extension instead, press star A.
f252	To respond to this message, press 1.
f253	Please enter month, day
f254	To play the active version, press 1.
f255	To delete this message, press star D.
f256	At beginning. To re-record, press 1. To play back, press 2-3.
f257	To use personal greeting, press Y. To use system greeting, press N.
f258	Message to
f259	scheduled for
f260	scheduled for
f261	rescheduled for
f262	received
f263	You are recording a subscriber name.
f264	Message not delivered because mailbox was full.

Fragment	Text
f265	Message not delivered because their mailboxes were full.
f266	was undeliverable
f267	Please enter extension
f268	To record another subscriber's name
f269	To play another subscriber's name
f270	subscriber ID
f271	Header
f272	Contact administrator for help.
f273	Please make your next entry
f274	Please make entry soon, or be disconnected.
f275	Cannot get your messages now, due to multiple logins to your mailbox.
f276	Time requested has passed, please re-schedule delivery.
f277	To exit directory, press pound.
f278	Please enter extension
f279	For active version, press 1.
f280	For administrative version, press 2.
f281	Message from
f282	To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
f283	Your mailbox is more than
f284	percent full. Please delete unneeded messages or greetings.
f285	To add a member, enter extension
f286	To add a member, enter last name
f287	Welcome to AUDIX.

Fragment	Text
f288	You are in the names directory. To find a subscriber's extension, enter the last name followed by the pound sign. To enter the letter Q, press 7; for Z, press 9. To look up by extension instead press star A.
f290	If you wish to specify a non-AUDIX subscriber, first change to extension addressing by pressing star A.
f291	To transfer to another extension, press star T.
f292	Louder, press 4. softer, press 7. faster, press 9. slower, press 8.
f293	Nothing to play back.
f294	To add entries, press 1.
f295	To re-enter list, press star L.
f296	To delete, press star D.
f297	To specify owner by extension, press star A.
f298	To specify owner by name, press star A.
f299	You are administering your greeting.
f300	A. M.
f301	P. M.
f302	You are recording announcement fragments. Enter fragment ID followed by pound sign. Refer to admin manual for correct ID.
f303	You are recording names. Enter extension
f304	To play back message, press 2-3. To delete your message, press star D. To approve your message, press pound.
f305	You are at the activity menu.
f306	You are changing your password.
f307	You are playing announcements.
f308	You are playing announcement fragments.
f309	You are playing names.

Fragment	Text
f310	January
f311	February
f312	March
f313	April
f314	May
f315	June
f316	July
f317	August
f318	September
f319	October
f320	November
f321	December
f322	You are in the numbers directory. To find a subscriber's name, enter the extension followed by the pound sign. To look up by name instead, press star A.
f323	You are responding to a piece of incoming mail.
f324	You are selecting which greeting will be played to callers. If you want your personal greeting to be played, press Y for yes. If you press N for no, the system greeting will be used.
f325	You are administering your lists. To create a mailing list, press 1. To play a summary of all your lists, press 2. To review a particular list, press 3.
f326	You are doing system administration. To record names, press 4. To play names, press 5. To record a machine name, press 6. To play a machine name, press 7. To record fragments, press 1. To play fragments, press 2. To play announcements, press 3.
f327	You are creating a mailing list.
f328	To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move onto the next step, press pound.

Fragment	Text
f329	You have not yet entered enough characters to identify a specific subscriber. To enter the letter Q, press 7; for Z press 9.
f330	Or enter just the pound sign if it's your phone.
f331	Personal greeting used.
f332	System greeting used.
f333	To add entries to the list or to change status of list, press 1.
f334	When finished addressing, press pound.
f335	When finished, press pound.
f336	To review addressees, press star 1.
f338	To play the administrative version, press 2.
f339	To replay the last few seconds, press 5. To advance a few seconds, press 6.
f340	Enter the hour, one through twelve, then two digits for the minutes, then A for AM or P for PM, and the pound sign.
f341	Enter the month, one through twelve, then two digits for the day of the month, then the pound sign.
f342	Electronic document communication
f343	Leave word calling
f344	Message Center Service
f345	Voice mail
f346	You are recording a machine name.
f347	You are adding a list.
f348	You are specifying a mailing list to review.
f349	To approve list as is, press pound.
f350	Sunday
f351	Monday
f352	Tuesday

Fragment	Text
f353	Wednesday
f354	Thursday
f355	Friday
f356	Saturday
f357	You are choosing between subscribers whose names match your entry. To indicate no subscribers match, delete your entry by pressing star D. To change to extension addressing and delete your entry, press star A.
f358	You are identifying a list as private or public.
f359	You are changing the status of your list. To modify status, press Y for yes or N for no.
f360	You are scanning mailing lists. To review list members, press zero. To rewind to previous list, press 2. To continue scanning lists, press 3.
f361	To skip to next list, press pound. To delete list, press star D.
f362	If you own the list, press pound. If someone else owns the list
f363	To approve the list you are creating, press pound.
f364	enter owner's extension
f365	enter owner's name
f366	To specify a different owner by extension, press star D.
f367	To specify a different owner by name, press star D.
f368	You are entering the number for a new list. Please enter a number up to six digits long
f369	To replace an existing list, enter that list's number,
f370	These are entries in your list.
f371	To rewind to current entry, press 2. To rewind to previous entries, press 2 as many times as necessary. To continue playback of list, press 3.
f372	To skip to next entry, press pound. To delete current entry, press star D.
f373	You are choosing whether to attach a copy of original message to your reply. To include the original, press Y for yes. To send only your reply, press N for no.

Fragment	Text
f374	You are choosing whether to file this message. To file a copy, press Y for yes. To send without filing a copy, press N for no.
f375	You are getting your incoming messages. To listen to the message, press zero. To respond to the message, press 1.
f376	To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.
f377	To delete message, press star D.
f378	You are checking the status of your outgoing messages.
f379	To delete status information, press star D.
f380	Please wait.
f381	To listen to the message, press zero. To re-record message before delivery, press 1.
f382	You are scheduling your message for delivery.
f383	Please enter hour, then two digits for minutes, then A for AM or P for PM, and pound sign.
f384	Please enter number of month, then two digits for day, and pound sign.
f385	To approve delivery time, press pound. To modify delivery time, press star D and listen for further instructions.
f386	Cannot change a delivered message.
f387	Message not delivered because recipient not found.
f388	To skip, press pound.
f389	To delete, press star D.
f390	oh
f391	one
f392	two
f393	three
f394	four

Fragment	Text
f395	five
f396	six
f397	seven
f398	eight
f399	nine
f400	ten
f401	eleven
f402	twelve
f403	thirteen
f404	fourteen
f405	fifteen
f406	sixteen
f407	seventeen
f408	eighteen
f409	nineteen
f410	twenty
f411	twenty-one
f412	twenty-two
f413	twenty-three
f414	twenty-four
f415	twenty-five
f416	twenty-six
f417	twenty-seven
f418	twenty-eight
f419	twenty-nine

Fragment	Text
f420	thirty
f421	thirty-one
f422	thirty-two
f423	thirty-three
f424	thirty-four
f425	thirty-five
f426	thirty-six
f427	thirty-seven
f428	thirty-eight
f429	thirty-nine
f430	forty
f431	forty-one
f432	forty-two
f433	forty-three
f434	forty-four
f435	forty-five
f436	forty-six
f437	forty-seven
f438	forty-eight
f439	forty-nine
f440	fifty
f441	fifty-one
f442	fifty-two
f443	fifty-three
f444	fifty-four

Fragment	Text
f445	fifty-five
f446	fifty-six
f447	fifty-seven
f448	fifty-eight
f449	fifty-nine
f450	sixty
f451	seventy
f452	eighty
f453	ninety
f454	hundred
f455	thousand
f456	million
f457	billion
f458	hundredth.
f459	thousandth.
f460	millionth.
f461	billionth.
f462	pound
f463	star
f464	Enter extension
f465	Enter last name
f466	created
f467	To begin recording, press one. After you finish recording, press one again.
f468	To continue playing, press 3.
f469	Enter owner's extension

Fragment	Text
f470	Enter owner's last name
f471	If it's your list, press pound.
f472	To approve, press pound. To record from here, press 1.
f473	filed messages
f474	To listen, press zero. To change or send again, press 1.
f475	To file a copy, press Y for yes or N for no.
f476	Message sent to
f477	Press 1 to select
f478	2 to select
f479	3 to select
f480	4 to select
f481	5 to select
f482	Press pound to select
f483	or enter more characters
f484	Enter more characters followed by the pound sign; if you just completed entering the last name, enter the first name.
f485	has
f486	To reply to sender by voice mail, press 1.
f487	To delete time, press star D. To default rest of the delivery time, press pound.
f488	To specify immediate delivery, press pound. Otherwise
f489	Otherwise, enter more characters of the name starting from where you left off.
f490	Please enter additional characters of the name, starting from where you left off.
f491	You are getting your incoming messages. To listen to the message, press zero. To respond to the message, press 1.
f492	Owner erased.
f493	You are requesting a transfer.

Fragment	Text
f494	private.
f495	public.
f496	Filed.
f497	To review your message, press star 1.
f498	Please enter a new list ID
f499	When finished recording, press pound to approve or 1 to edit your message.
f500	This is AUDIX.
f501	To record messages, press one. To get messages, press two. To administer attendant menu, press 3.
f502	To record attendant menu, press 1. To listen to attendant menu, press zero.
f503	You are administering your attendant menu.
f504	Transferring to an operator,
f505	You have selected an invalid option.
f506	Menu approved and activated.
f507	The person you called is not available. To leave a message, use touch tones to re-enter the number you called.
f508	Attendant Service not available. Try again later.
f509	System not administered for outcalling.
f510	Number
f511	If you do not have a touch tone phone,
f512	Your call is being transferred to an operator.
f513	Begin your message by saying the name and telephone number of the person you are calling. Someone will listen to the start of your message, and then forward the complete message to the person you called.
f514	otherwise
f515	To be transferred to an operator,
f516	To leave a message that will be delivered as soon as possible,

Fragment	Text
f517	You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.
f518	You are creating a voice message which will be delivered to the person specified in your message as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion.
f519	You are not authorized for outcalling.
f520	Your outcalling number,
f521	turned on
f522	turned off
f523	for
f524	to
f525	any time
f526	subject to administrator restrictions
f527	To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3.
f528	To turn on, press y. To turn off, press n.
f529	You are changing your outcalling options.
f530	Outcalling
f531	Enter outcalling number
f532	To change your outcalling phone number, press 1 and enter the number to be called followed by the pound sign. Anything you enter will be interpreted as a part of the called number. No global commands such as star H will be accepted at this time.
f533	Too many digits.
f534	Your outcalling number is
f535	For outcalling any time, press 1. For outcalling during prime time, press 2. To specify your times, press 3. For system outcalling schedule, press 4.
f536	You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator.

Fragment	Text
f537	Enter the starting hour, minutes, A or P, and pound sign.
f538	Enter the ending hour, minutes, A or P, and pound sign.
f539	The system allows outcalls from
f540	and from
f541	Up to
f542	digits may be used.
f543	To avoid further notification of these messages, press star pound. <BEEP>
f544	Outcalling specified for
f545	To delete own time, press star D.
f546	pause
f547	Good-bye
f548	You have no attendant menu.
f549	You are administering your attendant menu. To create attendant menu, press 1.
f550	To rewind your attendant menu, press two. To delete it, press star D. To stop playback of your attendant menu, press three.
f551	To access your messages,
f552	is not authorized to receive messages.
f553	You may enter another number
f554	To access your mailbox, press star R. To transfer to another extension, press star T.
f555	To access your mailbox, press star R.
f556	To exit, press star pound now.
f557	In most cases, entering a star or pound as the first digit will result in the star or pound being outpulsed. A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row.
f558	subject to administrator restrictions.
f559	A name cannot be recorded until the size of the names file system is increased.

Fragment	Text
f560	If you are programming a number to call a pager that requires a pound sign termination, press y to hear further help. Otherwise, press n to return to outcalling administration.
f561	You are addressing your message.
f562	Enter the
f563	digit extension
f564	There is no room in the mailbox to leave a message.
f565	Outcall canceled for new messages currently in mailbox.
f566	You are responding to an outcall notifying you of new messages.
f567	Either logging in or pressing star pound will result in the outcall being canceled for the new messages currently in your mailbox. If additional new messages arrive, another outcall will be scheduled."
f569	To modify, press one. If finished, press star pound.
f570	Recorded name too long
f571	Non-existent subscriber
f572	<i>not referenced</i>
f573	To record from here, press 1.
f574	Private
f575	Cannot forward a private message
f576	Recipients can forward this message
f577	To hold the message in its current category, press star star H.
f578	To skip to the next category, press star pound.
f579	Password must be
f580	Cannot attach a private message
f581	Press N now
f582	AUDIX passwords must now be at least
f583	After you finish recording, press 1 again.

Fragment	Text
f584	Message not delivered because special feature denied on recipients machine.
f585	Zero
f586	To skip, press pound.
f587	You are reviewing a list.
f588	or more digits.
f589	For pagers requiring a pound sign termination, start your number with a double pound sign. This will result in a single pound being outpulsed at the end of the digit string. Then, a star or pound in the next position will be interpreted as part of the outcalling number.
f590	A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row.
f591	To change your outcalling phone number, press one. To hear further instructions on programming a pager, press y. To return to outcalling administration, press n.
f592	AUDIX passwords must now be
f593	Please choose a new password of
f594	To delete, press star D. <BEEP>
f595	including
f600	New Broadcast messages.
f601	Priority
f602	other
f603	You also have
f604	As you use AUDIX, your name will be included in system announcements that you and other people will hear. Press 1, and at the tone, please speak your name. After speaking your name, press 1 again.
f605	Not private.
f606	To re-record your name, press 1. To approve, press pound.
f607	Name cannot be saved at this time. Please continue

Fragment	Text
f608	At the tone, please speak your name. After speaking your name, press 1.
f609	No room to save Broadcast message, so it will be retained in the new message category.
f610	You are recording your name. After you record your name, you can access other AUDIX features. As you use AUDIX, your name will be included in system announcements that you and other people will hear. Press 1 and at the tone, please speak your first and last name as you would like others to hear it. After speaking your name, press 1 again.
f611	You are recording your name. To record your name, press 1. After recording, press 1 again. To play back name, press 2-3. To approve, press pound.
f612	To make private, press 1.
f613	To make priority, press 2.
f614	To make broadcast, press 8.
f615	To make a login announcement, press 9.
f616	To exit options menu, press pound.
f617	To remove private status, press 1.
f618	To remove priority status, press 2.
f619	To remove broadcast status, press 8.
f620	To remove login announcement status, press 9.
f621	Private.
f622	Not Priority.
f623	Broadcast.
f624	Login announcement.
f625	To activate message waiting notification, press 1.
f626	To specify expiration date, press 2.
f627	To approve broadcast options, press pound.
f628	To deactivate message waiting notification, press 1.
f629	Please enter month, day, and pound sign.

Fragment	Text
f630	To change expiration date from
f631	Message waiting notification activated.
f632	Expiration date will be
f633	To make non-interruptible, press 1.
f634	To approve login announcement options, press pound.
f635	To remove non-interruptible status, press 1.
f636	Login announcement will be non-interruptible.
f637	Invalid date.
f638	is prior to delivery date, please re-schedule.
f639	Message cannot be both broadcast and priority.
f640	Message cannot be both a login announcement and priority.
f641	Message cannot be both a login announcement and private.
f642	Message cannot be both broadcast and a login announcement
f643	You are choosing options for this message. There are no options currently set.
f644	You are choosing options for this message. With the current settings,
f645	Private messages cannot be forwarded by the recipients.
f646	A priority message will be delivered before other messages and will be flagged for special attention in the recipient's mailbox.
f647	the message will be private.
f648	the message will be priority.
f649	the message will be broadcast.
f650	the message will be a login announcement.
f651	the message will be private and priority.
f652	A broadcast message is delivered to every subscriber on this machine. You may also address a broadcast message to subscribers on other machines.
f653	For broadcast options, press star M.

Fragment	Text
f654	the message will be broadcast and private.
f655	A login announcement will be played each time any subscriber logs onto this machine. You may also address a login message to subscribers on other machines.
f656	For login announcement options, press star M.
f657	You are choosing options for this broadcast message.
f658	Message waiting notification is currently not active.
f659	Message waiting notification will alert all local subscribers of this message. This option should be used sparingly, for it can impact system performance.
f660	Expiration date specifies the last day this broadcast message will be available to subscribers. The expiration date does not apply to a broadcast message already received by a subscriber and saved in their mailbox. The default expiration date is the second day after the scheduled delivery date.
f661	To approve these options, press pound.
f662	Message waiting notification is active.
f663	Message waiting notification is not active and this message has an expiration date of.
f664	Message waiting notification is active and this message has an expiration date of.
f665	You are choosing options for this login announcement.
f666	With the current settings, this login announcement will be non-interruptible.
f667	With the current settings, this login announcement will be interruptible.
f668	With the current settings, this login announcement will be non-interruptible and the login announcement has an expiration date of.
f669	With the current settings, this login announcement will be interruptible and the login announcement has an expiration date of.
f670	Non-interruptible status forces each subscriber to listen to the entire login announcement every time they log onto this machine.
f671	Expiration date specifies the last day this login announcement will be available to subscribers. The default expiration date is the second day after the scheduled delivery date.

Fragment	Text
f672	To address, please enter extensions and pound sign Or for options menu, press star M.
f673	To address, please enter names and pound sign Or for options menu, press star M.
f674	Due to sending restrictions, you cannot send messages to
f675	<i>not referenced</i>
f676	<i>not referenced</i>
f677	<i>not referenced</i>
f678	is past the expiration date, please reschedule.
f679	is not available. Sorry, you cannot leave a message now because this user's mailbox is full.
f680	is busy. Sorry, you cannot leave a message now because this user's mailbox is full.
f681	Sorry, cannot leave a message now because this user's mailbox is full.
f682	Broadcast message from
f683	Broadcaster has deleted this broadcast message.
f684	Private, broadcast message from
f685	Private, priority message from
f686	Private message from
f687	Undeliverable message notification received
f688	An undeliverable message was returned to your outgoing mailbox. To access your outgoing mailbox, press star R 4.
f689	Expiration time is
f690	Priority message from
f691	Login announcement from
f692	Broadcast message deleted.
f693	Broadcast message to all local subscribers
f694	Private, broadcast message to all local subscribers

Fragment	Text
f695	Private, priority message to
f696	Private message to
f697	Login announcement to all local subscribers
f698	Priority message to
f699	Message not delivered because another login announcement is active.
f700	To administer mailing lists, press 1. To administer personal directory, press 2.
f701	To change your password, press 4.
f702	To record your name, press 5.
f703	You are at subscriber administration.
f704	To create lists, press 1. To scan lists, press 2. To review and modify lists, press 3.
f705	Directory contains
f706	To add entries, press 1. To review all entries, press 2. To review a specific entry, press 3.
f707	If finished, press star pound.
f708	If finished adding entries, press pound.
f709	Enter alias for
f710	Enter next name and pound sign.
f711	Alias
f712	defined for
f713	Enter next extension and pound sign.
f714	Directory has no entries.
f715	Cannot add new entries because your directory is full.
f716	Alias must be ten or fewer numerals.
f717	Alias already defined.
f718	Name entered not followed by pound and not added to the directory.
f719	Extension entered not followed by pound and not added to the directory.

Fragment	Text
f720	Alias entered not followed by pound and not added to the directory.
f721	Directory is full.
f722	was not added to your personal directory.
f723	You are administering your personal directory.
f724	Personal directory review completed.
f725	You are adding entries to your personal directory.
f726	You are reviewing all entries in your personal directory.
f727	Enter alias and pound sign.
f728	deleted.
f729	You are reviewing a specific entry in your personal directory. To delete the current entry, press star D. To review another entry, enter the alias followed by the pound sign.
f730	Message not delivered because the broadcast mailbox was not defined.
f731	To record messages, press 1. To get messages, press 2.
f732	<i>not referenced</i>
f733	<i>not referenced</i>
f734	Private and priority.
f735	Broadcast and private.
f736	You are recording your name. As you use AUDIX, your name will be included in system announcements that you and other people will hear.
f737	Login announcement will be interruptible.
f738	Message not delivered due to sending restrictions.
f739	Message sent to all local subscribers.
f740	Private message sent to all local subscribers.
f741	Private, priority message sent to
f742	Private message sent to
f743	Priority message sent to

Fragment	Text
f744	For all calls,...
f745	active.
f746	<i>not referenced</i>
f747	For internal calls,...
f748	For external calls,...
f749	For busy calls,...
f750	For no answer calls,...
f751	For out-of-hours calls,...
f752	To listen to a greeting, press zero. To create, change, or delete a greeting, press 1. To scan all your greetings, press 2. To activate a greeting, press 3. To administer call types, press 4. If finished, press pound.
f753	Enter greeting number.
f754	Greeting
f755	not recorded.
f756	To listen to greeting
f757	To re-record, press 1.
f758	To delete, press star D.
f759	To review status, press 2.
f760	press zero.
f761	<i>not referenced</i>
f762	press 2.
f763	<i>not referenced</i>
f764	To use this greeting for all calls, press zero. For internal calls, press 1. For external calls, press 2.
f765	recorded, but not active
f766	To use this greeting for all calls, press 1.

Fragment	Text
f767	To use this greeting for all calls, press zero. For busy calls, press 1. For no answer calls, press 2.
f768	approved.
f769	Nothing to approve.
f770	recorded and active
f771	approved and active
f772	again
f773	To activate for out-of-hours calls, press 3.
f774	If you have addressed this message and wish to deliver it immediately, press star star pound.
f775	To record messages, press one. To get messages, press two. To administer personal greetings, press 3.
f776	the system greeting
f777	Cannot listen to system greeting.
f778	Cannot modify system greeting.
f779	No greetings recorded.
f780	Personal greetings review completed.
f781	To skip to the next greeting, press the pound sign.
f782	To activate a greeting, enter greeting number. To deactivate a greeting, activate a different greeting in its place.
f783	To activate another greeting, enter greeting number. To deactivate a greeting, activate a different greeting in its place.
f784	To activate system greeting, enter zero.
f785	Same greeting used for all calls.
f786	To identify calls as internal and external, press 1.
f787	To identify calls as busy and no answer, press 2.
f788	To identify calls as out-of-hours, press 3.

Fragment	Text
f789	Otherwise, press 4.
f790	Calls identified as internal and external.
f791	Calls identified as busy and no answer.
f792	Calls identified as out-of-hours.
f793	Calls not identified as out-of-hours.
f794	To change identification to busy and no answer, press 2.
f795	To change identification to internal and external, press 1.
f796	To remove out-of-hours identification, press 4.
f797	To use same greeting for all calls, press 5.
f798	Prime time is
f799	Enter last name
f800	You are specifying the expiration date.
f801	To respond to this notification, press one. To delete, press star D. To skip, press pound.
f802	Cannot send a message to the broadcast mailbox.
f803	<i>not referenced</i>
f804	not defined.
f805	For internal...
f806	For external...
f807	For busy...
f808	For no answer...
f809	internal
f810	external
f811	busy
f812	no answer
f813	and out-of-hours
f814	calls.

Fragment	Text
f815	You are administering your personal greetings.
f816	You are listening to a personal greeting.
f817	You are recording a personal greeting.
f818	You have just recorded
f819	You are scanning your personal greetings.
f820	You are selecting which greeting to activate.
f821	You are administering call types.
f822	As you use AUDIX your name will be included in system announcements that you and other people will hear. At the tone, please speak your name. After speaking your name, press one.
f823	for all calls
f824	for each call type
f825	for internal
f826	for external
f827	for busy
f828	for no answer
f829	for out-of-hours
f830	You must approve your recording.
f831	To exit the expiration date options, press star pound.
f832	Please enter extension and pound sign.
f833	To delete current entry, press star D.
f834	To delete this notification, press star D. To skip, press pound.
f835	for all new messages
f836	only for new priority messages
f837	To turn on Outcalling for all new messages, press 1. To turn on outcalling only for new priority messages, press 2.

Fragment	Text
f838	You are selecting which messages will receive outcalls.
f839	To rewind to the previous greeting, press 2.
f840	Option
f841	not defined
f842	Announcement not recorded. Try again later.
f843	To scan headers and messages, press 1. To scan headers only, press 2. To scan messages only, press 3.
f844	End of message.
f845	Next message.
f846	You are selecting an option for Automatic Message Scan.
f847	You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to or forward the message, press one.
f848	You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to the message, press one.
f849	To skip to the next message, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.
f850	Broadcast and Login Message services are not available.
f851	To skip, press pound.
f852	To rewind to the current entry, press 2. To rewind to previous entries, press 2 as many times as necessary.
f853	Messages skipped, retained as new.
f854	seconds to finish recording.
f855	remote AMIS mailbox ID
f856	This is a recorded message from
f857	from
f858	To replay, press zero.

Fragment	Text
f859	Mailbox ID not followed by pound.
f860	Mailbox ID not valid.
f861	AMIS
f862	It could not be delivered because the recipient appears to be a wrong number.
f863	It could not be delivered after multiple attempts to deliver the message.
f864	Automated call, please press 1 to disconnect.
f865	Your number was dialed by mistake. We're sorry for this inconvenience. To prevent this from recurring, this call has been reported as a misdialed call.
f866	AMIS casual subscribers cannot be added to your list.
f867	You are entering the
f868	Mailbox ID must be less than or equal to 16 digits.
f869	If the extension entered belongs to a casual AMIS subscriber, you will be prompted for a mailbox ID.
f870	The following message was restored.
f871	No message to restore.
f872	To undelete last deleted message, press star star U.
f900	zeroth.
f901	fortieth.
f902	fiftieth.
f903	sixtieth.
f904	seventieth.
f905	eightieth.
f906	ninetieth.
f907	hundredth.
f908	thousandth.

Fragment	Text
f909	millionth.
f910	billionth.
f913	If finished, press pound.
f914	not filed
f915	No options menu available.
f916	To send message, press pound Or enter a delivery option. To hear a list of options, press zero.
f917	To schedule delivery, press 3.
f918	To re-schedule delivery, press 3.
f919	To file a copy, press 4.
f920	To not file a copy, press 4.
f921	To make private, press 1. To send, press pound.
f922	To access the Delivery Options Menu, press "#" after recording your message.
f923	Press "#" to approve your message and access the Delivery Options Menu.
f924	seconds
f925	minutes
f926	<error sound>
f928	New Messages
f936	Partial entry deleted
f937	Sorry you are having difficulty. Please get help and try again later.
f938	first.
f939	second.
f940	third.
f941	fourth.
f942	fifth.
f943	sixth.

Fragment	Text
f944	seventh.
f945	eighth.
f946	ninth.
f947	tenth.
f948	eleventh.
f949	twelfth.
f950	thirteenth.
f951	fourteenth.
f952	fifteenth.
f953	sixteenth.
f954	seventeenth.
f955	eighteenth.
f956	nineteenth.
f957	twentieth.
f958	twenty-first.
f959	twenty-second.
f960	twenty-third.
f961	twenty-fourth.
f962	twenty-fifth.
f963	twenty-sixth.
f964	twenty-seventh.
f965	twenty-eighth.
f966	twenty-ninth.
f967	thirtieth.
f968	thirty-first.

Fragment	Text
f970	To continue reviewing, press 3. To delete an entry, press star D. If finished reviewing, press pound.
f971	To send, press pound.
f972	To reach the covering extension, press zero.
f973	If you are finished, please hang up.
f974	The return address for this message is not a valid extension.
f975	To return to getting messages, press pound.
f976	Name
f977	Not Broadcast
f978	Not Login Announcement

C. Fragment/Announcement Cross-Reference

This appendix provides a cross-referenced list of the standard system announcements that access each voiced fragment.

C-2 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
1	199
2	8
3	96
4	<i>not referenced</i>
5	301, 500
6	177, 184, 217
7	229
8	7, 20, 21, 25, 28, 29, 52, 201, 515, 517, 519, 521, 522, 524, 526, 528, 546, 1130
9	<i>not referenced</i>
10	181
11	184
12	43
13	58, 158, 501, 503, 509, 510, 513, 747, 750
14	117, 588
15	9
16	10
17	<i>not referenced</i>
18	7, 20, 201, 367, 515, 519
19	195
20	23
21	24, 132, 223, 1072, 1085, 1088
22	172, 215
23	221, 512, 932, 936
24	223, 258
25	340

Fragment	System Announcements That Use The Fragment
26	226
27	466
28	<i>not referenced</i>
29	15
30	258
31	16
32	17
33	254
34	249
35	19
36	502
37	255, 344
38	256, 345
39	500
40	22
41	28, 517, 521, 546
42	34
43	36, 709
44	33, 76
45	314, 539
46	35, 537, 543, 586, 746, 747
47	472
48	512, 701, 932, 933, 934, 936, 1038, 1049, 1050, 1051, 1052, 1053
49	84
50	302
51	30

C-4 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
52	<i>not referenced</i>
53	144
54	305
55	306
56	35, 44
57	1
58	574, 575, 1054, 1092
59	47
60	37
61	38
62	146, 147, 148, 149
63	138
64	182
65	40
66	41
67	141
68	230
69	231
70	232
71	505
72	45
73	2
74	48
75	350
76	31, 46, 1087

Fragment	System Announcements That Use The Fragment
77	49
78	303
79	53
80	101, 102, 227, 602, 746, 747, 749, 783, 784, 938, 939, 940, 1088
81	787
82	81
83	57
84	369
85	58
86	60, 1115
87	61, 78
88	13
89	64
90	65
91	26
92	67
93	310
94	70
95	14, 61, 119, 143, 228, 738, 757, 1064, 1087
96	116, 161, 227, 1186
97	240
98	50, 208
99	71
100	116, 755
101	73

C-6 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
102	315
103	74
104	77
105	101, 102, 120, 141, 142, 545, 547, 549, 702, 704, 727, 748, 751, 753, 754, 759, 935, 1058
106	79
107	115
108	508, 510
109	61, 119, 712, 770
110	82
111	83, 141, 341, 576, 608, 614, 616
112	76, 539
113	85
114	108
115	80, 88, 120, 545
116	107, 109
117	88, 529, 537, 545, 549, 736, 737, 746, 747, 775, 936, 938, 1049, 1050, 1053, 1058
118	89, 529, 531, 547, 549
119	120, 545, 547, 549
120	97
121	94, 112
122	92
123	93
124	106, 111, 1104
125	341
126	28, 517, 521, 546

Fragment	System Announcements That Use The Fragment
127	161
128	90, 551
129	90
130	95
131	11
132	98
133	106, 107
134	110
135	255, 256, 342, 343
136	124
137	<i>not referenced</i>
138	217
139	100
140	51
141	103
142	63, 64, 104, 196, 197, 206, 222, 1093, 1094, 1095, 1096, 1097, 1098
143	104, 196, 198, 222, 1093, 1094, 1095, 1096, 1097, 1098
144	95, 114
145	56
146	198, 200
147	353
148	596, 597, 618, 1055
149	131
150	127
151	<i>not referenced</i>

C-8 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
152	320
153	121
154	86
155	87
156	44, 122
157	122
158	119, 1099
159	126
160	6
161	129
162	<i>not referenced</i>
163	515, 517, 519, 521, 522, 524, 526, 528
164	32
165	132, 1072
166	133
167	134, 508
168	130, 756
169	159
170	136
171	137
172	139, 756
173	178
174	<i>not referenced</i>
175	89, 529
176	322

Fragment	System Announcements That Use The Fragment
177	151
178	153
179	241
180	152
181	69, 143, 145, 154
182	156
183	157
184	158
185	160
186	155
187	255, 256
188	163
189	164
190	165
191	166
192	167
193	318
194	168
195	169
196	170
197	62, 63, 64
198	356
199	171
200	172
201	140

Fragment	System Announcements That Use The Fragment
202	174
203	146, 147, 148
204	<i>not referenced</i>
205	<i>not referenced</i>
206	<i>not referenced</i>
207	150
208	175
209	176
210	530, 783
211	782
212	532, 784
213	179
214	309
215	149, 1011
216	307, 308
217	183
218	185
219	186
220	187, 525
221	540
222	536
223	544
224	10, 18, 65, 74, 80, 83, 88, 89, 108, 120, 141, 163, 177, 178, 179, 184, 187, 216, 217, 233, 316, 317, 319, 322, 340, 341, 344, 345, 346, 347, 357, 358, 506, 516, 518, 520, 523, 525, 529, 530, 531, 544, 545, 547, 549, 574, 575, 576, 582, 596, 597, 598, 600, 608, 610, 612, 614, 616, 733, 756, 772, 783, 872, 873, 1008, 1048, 1078, 1092, 1124

Fragment	System Announcements That Use The Fragment
225	329, 330, 604, 606, 618
226	189
227	190
228	192
229	348
230	193
231	105
232	69, 931
233	520, 523
234	202, 464
235	28, 29, 52, 184, 217, 500, 502, 504, 506, 517, 521, 524, 527, 528, 530, 532, 533, 534, 536, 538, 540, 544, 546, 568, 572, 574, 578, 580, 582, 584, 588, 590, 592, 596, 602, 604, 606, 610, 612, 614, 616, 618, 703, 736, 737, 748, 758, 775, 792, 1058
236	61, 119, 194, 712, 770
237	317, 319
238	142
239	709
240	349
241	109, 111
242	191
243	72, 128, 222
244	206
245	211
246	3
247	4
248	212

Fragment	System Announcements That Use The Fragment
249	213
250	214
251	529, 531
252	54
253	216
254	534, 538
255	132
256	203
257	313
258	282, 368
259	283
260	284, 308
261	285
262	287
263	501, 507
264	289
265	290
266	291
267	316, 317, 319
268	<i>not referenced</i>
269	<i>not referenced</i>
270	224
271	<i>not referenced</i>
272	14, 164
273	<i>not referenced</i>

Fragment	System Announcements That Use The Fragment
274	227, 712, 713
275	228
276	238
277	99, 101, 102
278	233, 516, 518, 756, 772
279	234
280	234
281	304
282	28, 29, 52, 120, 184, 217, 500, 502, 504, 506, 512, 517, 521, 524, 527, 528, 530, 532, 533, 534, 536, 538, 540, 544, 545, 546, 547, 549, 568, 572, 574, 578, 580, 582, 584, 588, 590, 592, 596, 604, 606, 610, 612, 614, 616, 618, 701, 703, 704, 736, 737, 748, 750, 751, 753, 754, 758, 759, 775, 792, 932, 933, 934, 935, 936, 1038, 1049, 1050, 1051, 1052, 1053, 1058
283	236
284	237
285	574, 575, 1092
286	596, 597
287	240
288	101
289	<i>not referenced</i>
290	547, 549
291	537, 543, 701, 746, 747, 932, 934, 936, 938, 940, 1049, 1050, 1052, 1053, 1182, 1186
292	68, 104, 500, 507, 508, 509, 510, 527, 548, 550, 552, 580, 584, 594, 703, 704, 747, 750, 792, 1036, 1069, 1070, 1093, 1094, 1095, 1096, 1097, 1098
293	248
294	220, 584

C-14 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
295	355
296	349, 508
297	600, 612
298	598, 610
299	500, 502
300	260
301	261
302	504
303	506
304	507, 509, 747, 750
305	512, 701, 932, 933, 934, 936, 1038, 1049, 1050, 1051, 1052, 1053
306	530, 532, 783, 784
307	538, 540
308	534, 536
309	544
310	270
311	271
312	272
313	273
314	274
315	275
316	276
317	277
318	278
319	279

Fragment	System Announcements That Use The Fragment
320	280
321	281
322	102
323	28, 29, 52, 517, 521, 524, 528, 546
324	568
325	1034
326	572
327	574, 596, 606
328	574, 575, 596, 597, 1092
329	606, 618, 1124
330	516, 520
331	311
332	312
333	527, 1073
334	5
335	91
336	4
337	<i>not referenced</i>
338	534, 538
339	68, 104, 500, 507, 508, 509, 510, 548, 552, 594, 703, 704, 1036, 1069, 1070, 1093, 1095, 1096, 1097, 1098
340	560
341	562
342	55
343	118

Fragment	System Announcements That Use The Fragment
344	123
345	235
346	503, 509
347	576, 598, 600, 608
348	610, 612, 614, 616, 618
349	109, 111, 255, 256
350	360
351	361
352	362
353	363
354	364
355	365
356	366
357	602
358	588
359	578
360	580
361	580
362	598, 600, 610, 612
363	576, 608, 614, 616
364	598, 610
365	600, 612
366	576, 614
367	608, 616
368	582

Fragment	System Announcements That Use The Fragment
369	582
370	527, 584
371	527, 584, 792
372	527, 584, 926, 1046
373	592
374	590
375	548, 1093
376	68, 548, 550, 552, 594
377	68, 104, 548, 552, 594, 1069, 1070, 1093, 1095, 1096, 1097, 1098
378	550, 552, 594, 1094, 1095, 1096
379	550, 1094
380	511, 765
381	552, 1095
382	560, 562
383	22
384	16, 1010
385	566
386	259
387	209, 262
388	24, 54, 104, 132, 173, 202, 223, 252, 253, 254, 257, 258, 469, 1093, 1094, 1095, 1096
389	24, 54, 59, 173, 202, 252, 257, 1072, 1086, 1088
390	390
391	391
392	392
393	393

Fragment	System Announcements That Use The Fragment
394	394
395	395
396	396
397	397
398	398
399	399
400	400
401	401
402	402
403	403
404	404
405	405
406	406
407	407
408	408
409	409
410	410
411	411
412	412
413	413
414	414
415	415
416	416
417	417
418	418

Fragment	System Announcements That Use The Fragment
419	419
420	420
421	421
422	422
423	423
424	424
425	425
426	426
427	427
428	428
429	429
430	430
431	431
432	432
433	433
434	434
435	435
436	436
437	437
438	438
439	439
440	440
441	441
442	442
443	443

Fragment	System Announcements That Use The Fragment
444	444
445	445
446	446
447	447
448	448
449	449
450	450
451	451
452	452
453	453
454	454
455	455
456	456
457	457
458	458
459	459
460	460
461	461
462	462
463	463
464	255, 342, 872
465	256, 343, 873
466	292
467	<i>not referenced</i>
468	180, 471

Fragment	System Announcements That Use The Fragment
469	344, 346, 357
470	345, 347, 358
471	344, 345, 346, 347, 357, 358
472	59, 471
473	468
474	257, 469, 594, 1096
475	467
476	<i>not referenced</i>
477	323
478	324
479	325
480	326
481	327
482	328
483	329, 604
484	330, 606, 618, 1124
485	66
486	21, 29, 201, 515, 517, 522, 524, 546
487	562
488	560
489	<i>not referenced</i>
490	<i>not referenced</i>
491	68, 104
492	354
493	547, 549, 769

Fragment	System Announcements That Use The Fragment
494	351
495	352
496	359
497	78, 507, 508, 509, 747, 750
498	18, 340
499	251
500	719
501	700, 701, 1038, 1050
502	702, 703, 704
503	703, 704
504	705
505	706
506	707
507	709, 714
508	738
509	741
510	711
511	712, 765
512	716
513	717
514	712
515	715
516	718
517	746, 749
518	747, 750

Fragment	System Announcements That Use The Fragment
519	720
520	721
521	722
522	723
523	724
524	725
525	726
526	727
527	728, 748, 751, 1058
528	729, 748, 751, 1058
529	748, 751, 1058
530	730
531	733
532	734
533	731
534	732
535	735, 736, 753
536	736, 737, 753, 754
537	739
538	740
539	742
540	743
541	744
542	745
543	756, 772

Fragment	System Announcements That Use The Fragment
544	766
545	737, 754
546	752
547	708, 1103
548	760
549	758, 759
550	703, 704
551	756, 772
552	762
553	763
554	<i>not referenced</i>
555	709, 749, 750, 938, 939, 940
556	761
557	734
558	767
559	710
560	734
561	575, 597, 1092
562	768, 769, 1078
563	80, 88, 120, 545
564	770
565	771
566	772
567	772
568	<i>not referenced</i>

Fragment	System Announcements That Use The Fragment
569	773
570	204
571	774
572	<i>not referenced</i>
573	507, 777
574	778
575	779
576	780
577	68, 104, 548, 1069, 1070, 1093, 1097, 1098
578	104, 1093, 1094, 1095, 1096, 1097, 1098
579	75
580	781
581	785
582	786
583	507
584	789
585	790
586	791, 792
587	792
588	793
589	764
590	764
591	788
592	794
593	795

Fragment	System Announcements That Use The Fragment
594	1085
595	12
596	<i>not referenced</i>
597	<i>not referenced</i>
598	<i>not referenced</i>
599	<i>not referenced</i>
600	800
601	801
602	802
603	803
604	804
605	1125
606	806
607	807
608	808
609	809
610	810
611	811
612	812
613	813
614	814
615	815
616	816
617	817, 1121
618	818

Fragment	System Announcements That Use The Fragment
619	819
620	820
621	821
622	1126
623	823
624	824
625	825
626	826
627	827
628	828
629	829
630	830
631	831
632	832
633	833
634	834
635	835
636	836
637	837
638	838
639	839
640	840
641	841
642	842
643	843

Fragment	System Announcements That Use The Fragment
644	844
645	845
646	846
647	847
648	848
649	849
650	850
651	851
652	852
653	853
654	854
655	855
656	856
657	857
658	858
659	859
660	860
661	861
662	862
663	863
664	864
665	865
666	866
667	867
668	868

Fragment	System Announcements That Use The Fragment
669	869
670	870
671	871
672	<i>not referenced</i>
673	<i>not referenced</i>
674	874
675	<i>not referenced</i>
676	<i>not referenced</i>
677	<i>not referenced</i>
678	878
679	879
680	880
681	881
682	882
683	883
684	884
685	885
686	886
687	887
688	888
689	889
690	890
691	891
692	892
693	893

Fragment	System Announcements That Use The Fragment
694	894
695	895
696	896
697	897
698	898
699	899
700	900
701	901
702	902
703	903
704	904
705	905
706	906
707	907
708	908
709	909
710	910
711	911
712	912
713	913
714	914
715	915
716	916
717	917
718	918

Fragment	System Announcements That Use The Fragment
719	919
720	920
721	921
722	922
723	923
724	924
725	925
726	926
727	927
728	928
729	929
730	930
731	933, 934, 1049
732	<i>not referenced</i>
733	<i>not referenced</i>
734	<i>not referenced</i>
735	<i>not referenced</i>
736	937
737	946
738	947
739	948
740	949
741	950
742	951
743	952

Fragment	System Announcements That Use The Fragment
744	953
745	954
746	<i>not referenced</i>
747	956
748	957
749	958
750	959
751	960
752	961
753	962
754	963
755	964
756	965
757	966
758	967, 1124
759	968
760	969
761	<i>not referenced</i>
762	971
763	<i>not referenced</i>
764	973
765	974
766	975
767	976
768	977

Fragment	System Announcements That Use The Fragment
769	978
770	979
771	980
772	981
773	982
774	983
775	984, 1051, 1052, 1053
776	985
777	986
778	987
779	988
780	989
781	990
782	991
783	992
784	993
785	994
786	995
787	996
788	997
789	998
790	999
791	1000
792	1001
793	1002

C-34 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
794	1003
795	1004
796	1005
797	1006
798	1007
799	1008
800	1009
801	1012
802	1013
803	<i>not referenced</i>
804	1015
805	1016
806	1017
807	1018
808	1019
809	1020
810	1021
811	1022
812	1023
813	1024
814	1025
815	1026
816	1027
817	1028
818	1029

Fragment	System Announcements That Use The Fragment
819	1030
820	1031
821	1032
822	1035
823	1037
824	<i>not referenced</i>
825	1039
826	1040
827	1041
828	1042
829	1043
830	1044
831	1045
832	1047
833	1054, 1055, 1079
834	<i>not referenced</i>
835	1056
836	1057
837	1059
838	1060
839	1061
840	1062
841	1063
842	1064
843	1065, 1068

Fragment	System Announcements That Use The Fragment
844	1066
845	1067
846	1068
847	1069, 1097
848	1070, 1098
849	1069, 1070
850	1071
851	1072, 1097, 1098
852	926
853	1074
854	1075
855	1078, 1079
856	1076
857	1084
858	1086
859	1089
860	1090
861	1077
862	1080
863	1081
864	1082
865	1083
866	1091
867	1079
868	1079, 1092

Fragment	System Announcements That Use The Fragment
869	1092
870	1100
871	1101
872	1102
873	<i>not referenced</i>
874	<i>not referenced</i>
875	<i>not referenced</i>
876	<i>not referenced</i>
877	<i>not referenced</i>
878	<i>not referenced</i>
879	<i>not referenced</i>
880	<i>not referenced</i>
881	<i>not referenced</i>
882	<i>not referenced</i>
883	<i>not referenced</i>
884	<i>not referenced</i>
885	<i>not referenced</i>
886	<i>not referenced</i>
887	<i>not referenced</i>
888	<i>not referenced</i>
889	<i>not referenced</i>
890	<i>not referenced</i>
891	<i>not referenced</i>
892	<i>not referenced</i>
893	<i>not referenced</i>

Fragment	System Announcements That Use The Fragment
894	<i>not referenced</i>
895	<i>not referenced</i>
896	<i>not referenced</i>
897	<i>not referenced</i>
898	<i>not referenced</i>
899	<i>not referenced</i>
900	1140
901	1172
902	1173
903	1174
904	1175
905	1176
906	1177
907	1178
908	1179
909	1180
910	1181
911	<i>not referenced</i>
912	<i>not referenced</i>
913	1122
914	1105
915	1106
916	1107
917	1108
918	1109

Fragment	System Announcements That Use The Fragment
919	1110
920	1111
921	1112
922	1113
923	1114
924	1116
925	1117
926	1118
927	<i>not referenced</i>
928	1119
929	<i>not referenced</i>
930	<i>not referenced</i>
931	<i>not referenced</i>
932	<i>not referenced</i>
933	<i>not referenced</i>
934	<i>not referenced</i>
935	<i>not referenced</i>
936	1120
937	1103
938	1141
939	1142
940	1143
941	1144
942	1145
943	1146

Fragment	System Announcements That Use The Fragment
944	1147
945	1148
946	1149
947	1150
948	1151
949	1152
950	1153
951	1154
952	1155
953	1156
954	1157
955	1158
956	1159
957	1160
958	1161
959	1162
960	1163
961	1164
962	1165
963	1166
964	1167
965	1168
966	1169
967	1170
968	1171

Fragment	System Announcements That Use The Fragment
969	<i>not referenced</i>
970	1104
971	1121, 1129
972	1183
973	1184
974	1185
975	20, 28, 29, 52, 517, 521, 524, 546, 1186
976	1123
977	1127
978	1128
979	<i>not referenced</i>
980	<i>not referenced</i>
981	<i>not referenced</i>
982	<i>not referenced</i>
983	<i>not referenced</i>
984	<i>not referenced</i>
985	<i>not referenced</i>
986	<i>not referenced</i>
987	<i>not referenced</i>
988	<i>not referenced</i>
989	<i>not referenced</i>
990	<i>not referenced</i>
991	<i>not referenced</i>
992	<i>not referenced</i>

Fragment	System Announcements That Use The Fragment
993	<i>not referenced</i>
994	<i>not referenced</i>
995	<i>not referenced</i>
996	<i>not referenced</i>
997	<i>not referenced</i>
998	<i>not referenced</i>
999	<i>not referenced</i>

Index

A

about this document *v*
active announcement set *1-2*
add fragment to announcement *2-5*
administration
 creating a new announcement version *3-5*
 customizing system announcements *2-1*
 delete old administrative copies *3-5*
 restoring customized announcements after an upgrade *3-1*
administrative announcement set *1-2*
announcement data (adat) filesystems *1-1*
announcement sets
 active *1-2*
 administrative *1-2*
 distribution on disks *1-3*
 standard (streamlined) *1-1*
 traditional (abbreviated) *1-1*
announcements
 announcement/fragment cross-reference *C-1*
 announcement/fragment text *A-1*
 defined *1-1*
 example of use *1-1*
 restoring after an upgrade *3-1, 3-6*
 standard announcements list *A-1*

B

backing up announcement sets *1-3*

C

Call Answer
 re-recording default greeting *2-1*
 restoring customized greeting after an upgrade *3-1*
changing fragments
 default Call Answer greeting *2-1*
 default Voice Mail greeting *2-1*
cross-referenced fragment/announcement table *C-1*
customizing system announcements

customizing system announcements—*Contd*
 overview of process *1-1, 1-3*
 procedures *2-1, 3-1, 3-7*

D

delete fragment from announcement *2-4*

F

filesystems
 announcement data (adat) *1-1*
 creating a new admin version *3-5, 3-6*
 delete old administrative copies *3-5*
 finding space for the admin version *3-5*
 finding the active version *2-2, 3-5*
 finding the admin version *2-2, 3-5*
 finding the temp version *3-5*
 updating the admin version *2-3, 2-4, 2-6, 3-7*
fragments
 add to an announcement *2-5*
 defined *1-1*
 delete from announcement *2-4*
 fragment text *B-1*
 fragment/announcement cross-reference *C-1*
 re-recording *2-1*
 restoring after an upgrade *3-6*
 standard fragments list *B-1*
 verifying impact on announcement set *3-1*

G

greetings
 re-recording default system greetings *2-1*
 restoring customized greetings after an upgrade *3-1*

R

re-recording default greeting *2-1*
re-recording fragments *2-1*

restoring system announcements
post-upgrade procedures *3-1*

S

streamlined user interface
standard announcement set *1-1*

T

traditional user interface
traditional announcement set *1-1*

U

upgrades
restoring customized
announcements/fragments *3-1, 3-6*
verifying customized announcement impact
3-1

V

Voice Mail
re-recording default greeting *2-1*
restoring customized greeting after an upgrade
3-1