

LINEMEN'S RUBBER GLOVES

NOTES CONCERNING THIS ADDENDUM

This addendum is being issued to cover the use of a commercial type rubber glove bag for carrying rubber gloves, and their associated B & C Leather Protector Gloves and C Fabric Liner Gloves, and also includes information on the periodic electrical test.

"See Addendum" should be marked in G81, 840.1 to indicate the following:

- Paragraph 1.04 - Added
- Paragraph 1.05 - Added
- Paragraph 2.06 - Replaced
- Paragraph 7.02(b) - Note added
- Paragraph 8.01 - Supplemented

1. GENERAL

1.04 Periodic Electrical Test - Except for the initial period, rubber gloves shall be returned for the periodic electrical test once every 6 months. The initial or first inspection period on new gloves is 8 months. New gloves will bear a "Return for Test" stamp showing a date 8 months after that in which the first test was made.

1.05 During the Periodic Electrical Test the rubber gloves are tested to withstand 10,000 volts alternating current for three minutes without excessive leakage.

The following electrical characteristics of typical higher voltage power circuits in this Area are being included to show that the standard Lineman's Rubber Gloves (tested at 10,000 volts) are designed to withstand the conductor to ground voltage of the power circuits with a nominal rating (conductor to conductor) up to and including 16,500 volts.

<u>Nominal Rating</u>	<u>Voltage Conductor to Conductor</u>	<u>Voltage Conductor to Ground</u>
12,000 Volts	12,000 Volts	6,920 Volts
16,500 "	16,500 "	9,530 "
34,500 "	34,500 "	19,900 "
66,000 "	66,000 "	38,000 "

2. DESCRIPTION

2.06 A commercial type rubber glove bag is provided for carrying and storing linemen's rubber gloves and associated leather protector and fabric liner gloves. It is a canvas bag equipped with snap hook for fastening bag to belt or tool bag.

7. CLEANING OF RUBBER GLOVES

7.02(b)

Note: The area on the glove where "Return for Test" or other stamps are located should not be cleaned.

8. DISPOSITION OF RUBBER GLOVES REQUIRING ELECTRICAL TEST

8.01 On receiving new or retested gloves, the gloves should be removed from the box and placed in the Rubber Glove Bag, and the box used for returning the old used gloves for retesting. The date on the box shall be made to agree with the "Return for Test" date stamped on the gloves.