

American Telephone and Telegraph Company

BELL SYSTEM PRACTICES
Teletypewriter Stations
Installation and
Maintenance

ADDENDUM P65.905
Issue A, 12-1-53
Long Lines Department
Dist. Class. 600AC

AUTOMATIC DIALER

TELERAPID TR-350

1. GENERAL

1.01 This addendum supplements Section P65.905, Issue A, to supply additional descriptive information and additional information on the cutting of code discs and the disposition of the test code disc.

1.02 The following paragraphs in Section P65.905 are affected:

Paragraph 2.01A -To follow Phg. 2.01
Paragraph 3.05 -Add paragraph (n)
Paragraph 3.11 -Replace with new Pgh.3.11
Paragraph 4.22(c)-Replace with new Pgh.4.22(c)

2. DESCRIPTION AND USE

2.01A (Add) The overall dimensions of the unit (without bracket) are 9-3/4 inches long, 4 inches high and 5 inches wide.

3. INSTALLATION

3.05 (n) (Add) Straighten any teeth that may have become bent or which are found out of line and as an added precaution, run the file gently over the tips and sides of the teeth to make sure there are no burs which might retard the rider shoe. This procedure is important.

3.11 (Replacing the text but retaining the figure)

The TR-350 dialer will replace the 5LA Dial (A) shown as Figure 3 of Section P90.980 and shall be connected to the 64C1 pulse dividing circuit through the three conductor cord described in Paragraph 3.01. Make connections as shown in Figure 3 of this section where the yellow and white wires will be the equivalent to the wires on the Y and B terminals of the 5LA dial and which are designated D and C. The blue wire of the cord will not be required and should be turned back and taped at the pulse divider.

4. MAINTENANCE

4.22 (c) (Replace) Install this test disc in position 25 of the indicator (49th position in the stack) and move the dial selector knob to select this disc. Leave this disc in this location and enter "TEST 0000000" in the corresponding space on the indicator card.

Note - Observe the cautions given in Paragraph 3.05 (n) when preparing this test disc.